



Complex IJ numbers

<https://maalchemist.ru/CIJ/>

Table of Contents

1	Definition	3
2	Addition and subtraction	3
3	Multiplication	3
4	Reciprocal	4
4.1	$\langle ij \rangle$	4
4.2	$\langle i \rangle$	4
4.3	$\langle j \rangle$	4
4.4	Exceptions	5
5	Conjugate $\langle ij \rangle$	6
5.1	6
5.2	6
6	Dot product $\langle u, v \rangle (+, +, +, +)$	6
7	Conjugate $\langle bcd \rangle$	7
7.1	7
7.2	7
7.3	7
7.4	7
8	Dot product $\langle u, v \rangle (+, -, -, -)$	8
9	Dot product $\langle u, v \rangle (+, +, +, -)$	8
10	Multiplication table	9
10.1	9
10.2	9
10.3	10
10.4	11
11	Exponential form	12
11.1	13
11.2	13
11.3	13
11.4	13
11.5	$R=0$	14
12	Conjugate \pm	15
12.1	$e+$	15
12.2	$e-$	15
13	Exponentiation	16
13.1	z^n	16
13.2	$\sqrt[n]{z}$	16
13.2.1	\sqrt{z}	16
13.2.2	$\sqrt[3]{z}$	17
14	Elementary functions	18
14.1	sin	18
14.2	cos	18
14.3	sinh	18
14.4	cosh	18
14.5	tan & Co.	19
14.6	inverse functions $\langle i \rangle$	19
14.7	normalized functions	19
14.8	exp	20
14.9	ln	20
15	Alternative notation	21

15.1	21
15.2	21
15.3	21
16	Dimension reduction	22
16.1	$xy:z\langle\cdot\rangle$	22
16.1.1	$xy:z\langle ab\rangle$	22
16.1.2	$xy:z\langle cd\rangle$	22
16.1.3	$xy:z\langle ba\rangle$	22
16.1.4	$xy:z\langle dc\rangle$	22
16.1.5	$xy:z\langle ac\rangle$	23
16.1.6	$xy:z\langle ca\rangle$	23
16.1.7	$xy:z\langle bd\rangle$	23
16.1.8	$xy:z\langle db\rangle$	23
16.2	$yz:x\langle\cdot\rangle$	24
16.3	$zx:y\langle\cdot\rangle$	24
17	Dimension reduction: $xy:z\langle ab\rangle$	25
17.1	Conjugate	25
17.2	Exponential form	25

1 Definition

$$z = (a + ib) + j(c + id) = a + ib + jc + ijd = r * e^{i\phi} + j \cdot \rho * e^{i\psi}$$

$$i^2 = -1$$

$$j^2 = -1$$

$$(ij)^2 = 1$$

$$i \cdot j = j \cdot i$$

$$e^{i\phi} = \cos \phi + i \cdot \sin \phi$$

$$e^{j\phi} = \cos \phi + j \cdot \sin \phi$$

$$e^{ij\phi} = \cosh \phi + ij \cdot \sinh \phi$$

$$a = r * \cos \phi$$

$$b = r * \sin \phi$$

$$c = \rho * \cos \psi$$

$$d = \rho * \sin \psi$$

2 Addition and subtraction

$$u = (a_1 + ib_1) + j(c_1 + id_1)$$

$$v = (a_2 + ib_2) + j(c_2 + id_2)$$

$$z = u + v = (a + ib) + j(c + id)$$

$$a = a_1 + a_2$$

$$b = b_1 + b_2$$

$$c = c_1 + c_2$$

$$d = d_1 + d_2$$

$$z = u - v = (a + ib) + j(c + id)$$

$$a = a_1 - a_2$$

$$b = b_1 - b_2$$

$$c = c_1 - c_2$$

$$d = d_1 - d_2$$

3 Multiplication

$$u = (a_1 + ib_1) + j(c_1 + id_1) = a_1 + ib_1 + jc_1 + ijd_1$$

$$v = (a_2 + ib_2) + j(c_2 + id_2) = a_2 + ib_2 + jc_2 + ijd_2$$

$$z = u * v = (a + ib) + j(c + id)$$

$$a = a_1 * a_2 - b_1 * b_2 - c_1 * c_2 + d_1 * d_2$$

$$b = a_1 * b_2 + b_1 * a_2 - c_1 * d_2 - d_1 * c_2$$

$$c = a_1 * c_2 - b_1 * d_2 + c_1 * a_2 - d_1 * b_2$$

$$d = a_1 * d_2 + b_1 * c_2 + c_1 * b_2 + d_1 * a_2$$

$$(a + ib) * (a - ib) = a^2 + b^2$$

$$(a + jb) * (a - jb) = a^2 + b^2$$

$$(a + ijb) * (a - ijb) = a^2 - b^2$$

$$(a + ib + jc + ijd) * (a + ib + jc + ijd) = a^2 - b^2 - c^2 + d^2 + i \cdot 2(ab - cd) + j \cdot 2(ac - bd) + ij \cdot 2(ad + bc) = z^2$$

$$(a + ib + jc + ijd) * (a + ib - jc - ijd) = a^2 - b^2 + c^2 - d^2 + i \cdot 2(ab + cd)$$

$$(a + ib + jc + ijd) * (a - ib + jc - ijd) = a^2 + b^2 - c^2 - d^2 + j \cdot 2(ac + bd)$$

$$(a + ib + jc + ijd) * (a - ib - jc + ijd) = a^2 + b^2 + c^2 + d^2 + ij \cdot 2(ad - bc)$$

$$(a + ib + jc + ijd) * (a + ib + jc - ijd) = a^2 - b^2 - c^2 - d^2 + i \cdot 2ab + j \cdot 2ac + ij \cdot 2bc$$

$$(a + ib + jc + ijd) * (a + ib - jc + ijd) = a^2 - b^2 + c^2 + d^2 + i \cdot 2ab - j \cdot 2bd + ij \cdot 2ad$$

$$(a + ib + jc + ijd) * (a - ib + jc + ijd) = a^2 + b^2 - c^2 + d^2 - i \cdot 2cd + j \cdot 2ac + ij \cdot 2ad$$

$$(a + ib + jc + ijd) * (a - ib - jc - ijd) = a^2 + b^2 + c^2 - d^2 + i \cdot 2cd + j \cdot 2bd - ij \cdot 2bc$$

4 Reciprocal

4.1 <ij>

$$(a + ib + jc + ijd) * (a - ib - jc + ijd) = a^2 + b^2 + c^2 + d^2 + ij \cdot 2(ad - bc)$$

$$\frac{1}{a + ib + jc + ijd} = \underline{a} + i\underline{b} + j\underline{c} + i\underline{d} = \frac{a - ib - jc + ijd}{a^2 + b^2 + c^2 + d^2 + ij \cdot 2(ad - bc)}$$

$$V = a^2 + b^2 + c^2 + d^2$$

$$V - U = (a - d)^2 + (b + c)^2$$

$$U = 2(ad - bc)$$

$$V + U = (a + d)^2 + (b - c)^2$$

$$F = 1 / (V^2 - U^2)$$

$$V^2 - U^2 = ((a - d)^2 + (b + c)^2) * ((a + d)^2 + (b - c)^2)$$

$$\frac{1}{a + ib + jc + ijd} = \frac{a - ib - jc + ijd}{V + ijU} = \frac{(a - ib - jc + ijd) * (V - ijU)}{V^2 - U^2}$$

$$(a - ib - jc + ijd) * (V - ijU) = (aV - dU) + i \cdot (-bV - cU) + j \cdot (-bU - cV) + ij \cdot (-aU + dV)$$

$$\underline{a} = F * (aV - dU) = F * (aV - dU)$$

$$\underline{b} = F * (-bV - cU) = F * (-bV - cU)$$

$$\underline{c} = F * (-bU - cV) = F * (-cV - bU)$$

$$\underline{d} = F * (-aU + dV) = F * (dV - aU)$$

$$\underline{a} + \underline{d} = F * (V * (a + d) - U * (a + d)) = F * (V - U) * (a + d)$$

$$\underline{b} - \underline{c} = -F * (V * (b - c) - U * (b - c)) = -F * (V - U) * (b - c)$$

$$\underline{a} - \underline{d} = F * (V * (a - d) + U * (a - d)) = F * (V + U) * (a - d)$$

$$\underline{b} + \underline{c} = -F * (V * (b + c) + U * (b + c)) = -F * (V + U) * (b + c)$$

4.2 <i>

$$(a + ib + jc + ijd) * (a + ib - jc - ijd) = a^2 - b^2 + c^2 - d^2 + i \cdot 2(ab + cd)$$

$$\frac{1}{a + ib + jc + ijd} = \underline{a} + i\underline{b} + j\underline{c} + i\underline{d} = \frac{a + ib - jc - ijd}{a^2 - b^2 + c^2 - d^2 + i \cdot 2(ab + cd)}$$

$$V = a^2 - b^2 + c^2 - d^2$$

$$U = 2(ab + cd)$$

$$F = 1 / (V^2 + U^2)$$

$$\frac{1}{a + ib + jc + ijd} = \frac{a + ib - jc - ijd}{V + iU} = \frac{(a + ib - jc - ijd) * (V - iU)}{V^2 + U^2}$$

$$(a + ib - jc - ijd) * (V - iU) = (aV + bU) + i \cdot (-aU + bV) + j \cdot (-cV - dU) + ij \cdot (cU - dV)$$

$$\underline{a} = F * (aV + bU) = F * (aV + bU)$$

$$\underline{b} = F * (-aU + bV) = F * (bV - aU)$$

$$\underline{c} = F * (-cV - dU) = F * (-cV - dU)$$

$$\underline{d} = F * (cU - dV) = F * (-dV + cU)$$

4.3 <j>

$$(a + ib + jc + ijd) * (a - ib + jc - ijd) = a^2 + b^2 - c^2 - d^2 + j \cdot 2(ac + bd)$$

$$\frac{1}{a + ib + jc + ijd} = \underline{a} + i\underline{b} + j\underline{c} + i\underline{d} = \frac{a - ib + jc - ijd}{a^2 + b^2 - c^2 - d^2 + j \cdot 2(ac + bd)}$$

$$V = a^2 + b^2 - c^2 - d^2$$

$$U = 2(ac + bd)$$

$$F = 1 / (V^2 + U^2)$$

$$\frac{1}{a + ib + jc + ijd} = \frac{a - ib + jc - ijd}{V + jU} = \frac{(a - ib + jc - ijd) * (V - jU)}{V^2 + U^2}$$

$$(a - ib + jc - ijd) * (V - jU) = (aV + cU) + i \cdot (-bV - dU) + j \cdot (-aU + cV) + ij \cdot (bU - dV)$$

$$\underline{a} = F * (aV + cU) = F * (aV + cU)$$

$$\underline{b} = F * (-bV - dU) = F * (-bV - dU)$$

$$\underline{c} = F * (-aU + cV) = F * (cV - aU)$$

$$\underline{d} = F * (bU - dV) = F * (-dV + bU)$$

4.4 Exceptions

$$z = a + ib + jc + ijd = (a + ib) + j(c + id)$$

$$1/z = \underline{a} + i\underline{b} + j\underline{c} + i\underline{d}$$

$$\underline{a} = F * (aV - dU)$$

$$\underline{b} = F * (-bV - cU)$$

$$\underline{c} = F * (-cV - bU)$$

$$\underline{d} = F * (dV - aU)$$

$$V = a^2 + b^2 + c^2 + d^2$$

$$U = 2 \cdot (ad - bc)$$

$$F = 1 / (V^2 - U^2)$$

$$V - U = (a - d)^2 + (b + c)^2$$

$$V + U = (a + d)^2 + (b - c)^2$$

$$V^2 - U^2 = ((a - d)^2 + (b + c)^2) * ((a + d)^2 + (b - c)^2)$$

1) $a = d \neq 0 \wedge b = -c \neq 0$

$$z = a(1 + ij) + b(i - j) = a + ib - jb + ija = (a + ib) + j(-b + ia)$$

2) $a = -d \neq 0 \wedge b = c \neq 0$

$$z = a(1 - ij) + b(i + j) = a + ib + jb - ija = (a + ib) + j(b - ia)$$

3) $a = d = 0 \wedge b = c \neq 0$

$$z = b(i + j) = ib + jb$$

4) $a = d = 0 \wedge b = -c \neq 0$

$$z = b(i - j) = ib - jb$$

5) $b = c = 0 \wedge a = d \neq 0$

$$z = a(1 + ij) = a + ija$$

6) $b = c = 0 \wedge a = -d \neq 0$

$$z = a(1 - ij) = a - ija$$

7) $a = b = c = d = 0$

$$z = 0$$

5 Conjugate $\langle ij \rangle$

5.1

$$\begin{aligned} z &= (a + ib) + j(c + id) = a + ib + jc + ijd \\ \bar{z}_i &= (a - ib) + j(c - id) = a - ib + jc - ijd \\ \bar{z}_j &= (a + ib) - j(c + id) = a + ib - jc - ijd \\ \bar{z}_{ij} &= (a - ib) - j(c - id) = a - ib - jc + ijd \end{aligned}$$

5.2

$$\begin{aligned} z * \bar{z}_i &= (a + ib + jc + ijd) * (a - ib + jc - ijd) = a^2 + b^2 - c^2 - d^2 + j \cdot 2(ac + bd) \\ z * \bar{z}_j &= (a + ib + jc + ijd) * (a + ib - jc - ijd) = a^2 - b^2 + c^2 - d^2 + i \cdot 2(ab + cd) \\ z * \bar{z}_{ij} &= (a + ib + jc + ijd) * (a - ib - jc + ijd) = a^2 + b^2 + c^2 + d^2 + ij \cdot 2(ad - bc) \end{aligned}$$

$$\begin{aligned} \bar{z}_{ij} * \bar{z}_i &= (a - ib - jc + ijd) * (a - ib + jc - ijd) = a^2 - b^2 + c^2 - d^2 - i \cdot 2(ab + cd) \\ \bar{z}_{ij} * \bar{z}_j &= (a - ib - jc + ijd) * (a + ib - jc - ijd) = a^2 + b^2 - c^2 - d^2 - j \cdot 2(ac + bd) \\ \bar{z}_i * \bar{z}_j &= (a - ib + jc - ijd) * (a + ib - jc - ijd) = a^2 + b^2 + c^2 + d^2 - ij \cdot 2(ad - bc) \end{aligned}$$

$$\frac{1}{2} (z * \bar{z}_{ij} + \bar{z}_i * \bar{z}_j) = a^2 + b^2 + c^2 + d^2$$

$$\frac{1}{2} (z * \bar{z}_i + \bar{z}_{ij} * \bar{z}_j) = a^2 + b^2 - c^2 - d^2$$

$$\frac{1}{2} (z * \bar{z}_j + \bar{z}_{ij} * \bar{z}_i) = a^2 - b^2 + c^2 - d^2$$

6 Dot product $\langle u, v \rangle$ (+, +, +, +)

$$\begin{aligned} z &= a + ib + jc + ijd \\ \bar{z}_{ij} &= a - ib - jc + ijd \\ \bar{z}_i &= a - ib + jc - ijd \\ \bar{z}_j &= a + ib - jc - ijd \end{aligned}$$

$$\begin{aligned} u &= a_1 + ib_1 + jc_1 + ijd_1 \\ \bar{u}_{ij} &= a_1 - ib_1 - jc_1 + ijd_1 \\ \bar{u}_i &= a_1 - ib_1 + jc_1 - ijd_1 \\ \bar{u}_j &= a_1 + ib_1 - jc_1 - ijd_1 \end{aligned}$$

$$\begin{aligned} v &= a_2 + ib_2 + jc_2 + ijd_2 \\ \bar{v}_{ij} &= a_2 - ib_2 - jc_2 + ijd_2 \\ \bar{v}_i &= a_2 - ib_2 + jc_2 - ijd_2 \\ \bar{v}_j &= a_2 + ib_2 - jc_2 - ijd_2 \end{aligned}$$

$$\langle u, v \rangle \stackrel{\text{def}}{=} \frac{1}{4} \left((u * \bar{v}_{ij} + v * \bar{u}_{ij}) + (\bar{u}_i * \bar{v}_j + \bar{v}_i * \bar{u}_j) \right)$$

$$\langle u, v \rangle = a_1 a_2 + b_1 b_2 + c_1 c_2 + d_1 d_2$$

$$\langle z, z \rangle \stackrel{\text{def}}{=} \frac{1}{2} (z * \bar{z}_{ij} + \bar{z}_i * \bar{z}_j)$$

$$\langle z, z \rangle = a^2 + b^2 + c^2 + d^2$$

7 Conjugate $\langle bcd \rangle$

7.1

$$\begin{aligned}
 z &= a + ib + jc + ijd \\
 \bar{z}_d &= a + ib + jc - ijd \\
 \bar{z}_c &= a + ib - jc + ijd \\
 \bar{z}_{cd} &= a + ib - jc - ijd = \bar{z}_j = (a + ib) - j(c + id) \\
 \bar{z}_b &= a - ib + jc + ijd \\
 \bar{z}_{bd} &= a - ib + jc - ijd = \bar{z}_i = (a - ib) + j(c - id) \\
 \bar{z}_{bc} &= a - ib - jc + ijd = \bar{z}_{ij} = (a - ib) - j(c - id) \\
 \bar{z}_{bcd} &= a - ib - jc - ijd
 \end{aligned}$$

7.2

$$\begin{aligned}
 z * \bar{z}_d &= a^2 - b^2 - c^2 - d^2 + i \cdot (+2ab) + j \cdot (+2ac) + ij \cdot (+2bc) \\
 \bar{z}_{bc} * \bar{z}_{bcd} &= a^2 - b^2 - c^2 - d^2 + i \cdot (-2ab) + j \cdot (-2ac) + ij \cdot (+2bc) \\
 \bar{z}_{bd} * \bar{z}_b &= a^2 - b^2 - c^2 - d^2 + i \cdot (-2ab) + j \cdot (+2ac) + ij \cdot (-2bc) \\
 \bar{z}_{cd} * \bar{z}_c &= a^2 - b^2 - c^2 - d^2 + i \cdot (+2ab) + j \cdot (-2ac) + ij \cdot (-2bc)
 \end{aligned}$$

$$\frac{1}{4} (z * \bar{z}_d + \bar{z}_{bc} * \bar{z}_{bcd} + \bar{z}_{bd} * \bar{z}_b + \bar{z}_{cd} * \bar{z}_c) = (a^2 - b^2 - c^2 - d^2)$$

7.3

$$\begin{aligned}
 z * \bar{z}_{bcd} &= a^2 + b^2 + c^2 - d^2 + i \cdot (+2cd) + j \cdot (+2bd) + ij \cdot (-2bc) \\
 \bar{z}_{bc} * \bar{z}_d &= a^2 + b^2 + c^2 - d^2 + i \cdot (-2cd) + j \cdot (-2bd) + ij \cdot (-2bc) \\
 \bar{z}_{bd} * \bar{z}_c &= a^2 + b^2 + c^2 - d^2 + i \cdot (-2cd) + j \cdot (+2bd) + ij \cdot (+2bc) \\
 \bar{z}_{cd} * \bar{z}_b &= a^2 + b^2 + c^2 - d^2 + i \cdot (+2cd) + j \cdot (-2bd) + ij \cdot (+2bc)
 \end{aligned}$$

$$\frac{1}{4} (z * \bar{z}_{bcd} + \bar{z}_{bc} * \bar{z}_d + \bar{z}_{bd} * \bar{z}_c + \bar{z}_{cd} * \bar{z}_b) = (a^2 + b^2 + c^2 - d^2)$$

7.4

$$\begin{aligned}
 z &= a + ib + jc + ijd \\
 u &= a_1 + ib_1 + jc_1 + ijd_1 \\
 v &= a_2 + ib_2 + jc_2 + ijd_2
 \end{aligned}$$

$$\frac{1}{4} (z * \bar{z}_d + \bar{z}_{bc} * \bar{z}_{bcd} + \bar{z}_{bd} * \bar{z}_b + \bar{z}_{cd} * \bar{z}_c) = (a^2 - b^2 - c^2 - d^2)$$

$$\frac{1}{8} \left((u * \bar{v}_d + v * \bar{u}_d) + (\bar{u}_{bc} * \bar{v}_{bcd} + \bar{v}_{bc} * \bar{u}_{bcd}) + (\bar{u}_{bd} * \bar{v}_b + \bar{v}_{bd} * \bar{u}_b) + (\bar{u}_{cd} * \bar{v}_c + \bar{v}_{cd} * \bar{u}_c) \right) = (a_1 a_2 - b_2 b_2 - c_1 c_2 - d_1 d_2)$$

$$\frac{1}{4} (z * \bar{z}_{bcd} + \bar{z}_{bc} * \bar{z}_d + \bar{z}_{bd} * \bar{z}_c + \bar{z}_{cd} * \bar{z}_b) = (a^2 + b^2 + c^2 - d^2)$$

$$\frac{1}{8} \left((u * \bar{v}_{bcd} + v * \bar{u}_{bcd}) + (\bar{u}_{bc} * \bar{v}_d + \bar{v}_{bc} * \bar{u}_d) + (\bar{u}_{bd} * \bar{v}_c + \bar{v}_{bd} * \bar{u}_c) + (\bar{u}_{cd} * \bar{v}_b + \bar{v}_{cd} * \bar{u}_b) \right) = (a_1 a_2 + b_2 b_2 + c_1 c_2 - d_1 d_2)$$

8 Dot product $\langle u, v \rangle$ $(+, -, -, -)$

$$\begin{aligned} z &= a + ib + jc + id \\ u &= a_1 + ib_1 + jc_1 + id_1 \\ v &= a_2 + ib_2 + jc_2 + id_2 \end{aligned}$$

$$\begin{aligned} \langle u, v \rangle &\stackrel{\text{def}}{=} \frac{1}{8} \left((u * \bar{v}_d + v * \bar{u}_d) + (\bar{u}_{bc} * \bar{v}_{bcd} + \bar{v}_{bc} * \bar{u}_{bcd}) + (\bar{u}_{bd} * \bar{v}_b + \bar{v}_{bd} * \bar{u}_b) + (\bar{u}_{cd} * \bar{v}_c + \bar{v}_{cd} * \bar{u}_c) \right) \\ \langle u, v \rangle &= a_1 a_2 - b_1 b_2 - c_1 c_2 - d_1 d_2 \end{aligned}$$

$$\begin{aligned} \langle z, z \rangle &\stackrel{\text{def}}{=} \frac{1}{4} (z * \bar{z}_d + \bar{z}_{bc} * \bar{z}_{bcd} + \bar{z}_{bd} * \bar{z}_b + \bar{z}_{cd} * \bar{z}_c) \\ \langle z, z \rangle &= a^2 - b^2 - c^2 - d^2 \end{aligned}$$

9 Dot product $\langle u, v \rangle$ $(+, +, +, -)$

$$\begin{aligned} z &= a + ib + jc + id \\ u &= a_1 + ib_1 + jc_1 + id_1 \\ v &= a_2 + ib_2 + jc_2 + id_2 \end{aligned}$$

$$\begin{aligned} \langle u, v \rangle &\stackrel{\text{def}}{=} \frac{1}{8} \left((u * \bar{v}_{bcd} + v * \bar{u}_{bcd}) + (\bar{u}_{bc} * \bar{v}_d + \bar{v}_{bc} * \bar{u}_d) + (\bar{u}_{bd} * \bar{v}_c + \bar{v}_{bd} * \bar{u}_c) + (\bar{u}_{cd} * \bar{v}_b + \bar{v}_{cd} * \bar{u}_b) \right) \\ \langle u, v \rangle &= a_1 a_2 + b_1 b_2 + c_1 c_2 - d_1 d_2 \end{aligned}$$

$$\begin{aligned} \langle z, z \rangle &\stackrel{\text{def}}{=} \frac{1}{4} (z * \bar{z}_{bcd} + \bar{z}_{bc} * \bar{z}_d + \bar{z}_{bd} * \bar{z}_c + \bar{z}_{cd} * \bar{z}_b) \\ \langle z, z \rangle &= a^2 + b^2 + c^2 - d^2 \end{aligned}$$

10 Multiplication table

10.1

$$\begin{aligned}
 z &= a + ib + jc + ijd \\
 \bar{z}_d &= a + ib + jc - ijd \\
 \bar{z}_c &= a + ib - jc + ijd \\
 \bar{z}_{cd} &= a + ib - jc - ijd = \bar{z}_j = (a + ib) - j(c + id) \\
 \bar{z}_b &= a - ib + jc + ijd \\
 \bar{z}_{bd} &= a - ib + jc - ijd = \bar{z}_i = (a - ib) + j(c - id) \\
 \bar{z}_{bc} &= a - ib - jc + ijd = \bar{z}_{ij} = (a - ib) - j(c - id) \\
 \bar{z}_{bcd} &= a - ib - jc - ijd
 \end{aligned}$$

10.2

$$\begin{aligned}
 z * z &= a^2 - b^2 - c^2 + d^2 + i \cdot (+2(ab - cd)) + j \cdot (+2(ac - bd)) + ij \cdot (+2(ad + bc)) \\
 z * \bar{z}_d &= a^2 - b^2 - c^2 - d^2 + i \cdot (+2ab) + j \cdot (+2ac) + ij \cdot (+2bc) \\
 z * \bar{z}_c &= a^2 - b^2 + c^2 + d^2 + i \cdot (+2ab) + j \cdot (-2bd) + ij \cdot (+2ad) \\
 z * \bar{z}_{cd} &= a^2 - b^2 + c^2 - d^2 + i \cdot (+2(ab + cd)) \\
 z * \bar{z}_b &= a^2 + b^2 - c^2 + d^2 + i \cdot (-2cd) + j \cdot (+2ac) + ij \cdot (+2ad) \\
 z * \bar{z}_{bd} &= a^2 + b^2 - c^2 - d^2 + j \cdot (+2(ac + bd)) \\
 z * \bar{z}_{bc} &= a^2 + b^2 + c^2 + d^2 + ij \cdot (+2(ad - bc)) \\
 z * \bar{z}_{bcd} &= a^2 + b^2 + c^2 - d^2 + i \cdot (+2cd) + j \cdot (+2bd) + ij \cdot (-2bc)
 \end{aligned}$$

$$\begin{aligned}
 \bar{z}_d * z &= a^2 - b^2 - c^2 - d^2 + i \cdot (+2ab) + j \cdot (+2ac) + ij \cdot (+2bc) \\
 \bar{z}_d * \bar{z}_d &= a^2 - b^2 - c^2 + d^2 + i \cdot (+2(ab + cd)) + j \cdot (+2(ac + bd)) + ij \cdot (-2(ad - bc)) \\
 \bar{z}_d * \bar{z}_c &= a^2 - b^2 + c^2 - d^2 + i \cdot (+2(ab - cd)) \\
 \bar{z}_d * \bar{z}_{cd} &= a^2 - b^2 + c^2 + d^2 + i \cdot (+2ab) + j \cdot (+2bd) + ij \cdot (-2ad) \\
 \bar{z}_d * \bar{z}_b &= a^2 + b^2 - c^2 - d^2 + j \cdot (+2(ac - bd)) \\
 \bar{z}_d * \bar{z}_{bd} &= a^2 + b^2 - c^2 + d^2 + i \cdot (+2cd) + j \cdot (+2ac) + ij \cdot (-2ad) \\
 \bar{z}_d * \bar{z}_{bc} &= a^2 + b^2 + c^2 - d^2 + i \cdot (-2cd) + j \cdot (-2bd) + ij \cdot (-2bc) \\
 \bar{z}_d * \bar{z}_{bcd} &= a^2 + b^2 + c^2 + d^2 + ij \cdot (-2(ad + bc))
 \end{aligned}$$

$$\begin{aligned}
 \bar{z}_c * z &= a^2 - b^2 + c^2 + d^2 + i \cdot (+2ab) + j \cdot (-2bd) + ij \cdot (+2ad) \\
 \bar{z}_c * \bar{z}_d &= a^2 - b^2 + c^2 - d^2 + i \cdot (+2(ab - cd)) \\
 \bar{z}_c * \bar{z}_c &= a^2 - b^2 - c^2 + d^2 + i \cdot (+2(ab + cd)) + j \cdot (-2(ac + bd)) + ij \cdot (+2(ad - bc)) \\
 \bar{z}_c * \bar{z}_{cd} &= a^2 - b^2 - c^2 - d^2 + i \cdot (+2ab) + j \cdot (-2ac) + ij \cdot (-2bc) \\
 \bar{z}_c * \bar{z}_b &= a^2 + b^2 + c^2 + d^2 + ij \cdot (+2(ad + bc)) \\
 \bar{z}_c * \bar{z}_{bd} &= a^2 + b^2 + c^2 - d^2 + i \cdot (-2cd) + j \cdot (+2bd) + ij \cdot (+2bc) \\
 \bar{z}_c * \bar{z}_{bc} &= a^2 + b^2 - c^2 + d^2 + i \cdot (+2cd) + j \cdot (-2ac) + ij \cdot (+2ad) \\
 \bar{z}_c * \bar{z}_{bcd} &= a^2 + b^2 - c^2 - d^2 + j \cdot (-2(ac - bd))
 \end{aligned}$$

$$\begin{aligned}
 \bar{z}_{cd} * z &= a^2 - b^2 + c^2 - d^2 + i \cdot (+2(ab + cd)) \\
 \bar{z}_{cd} * \bar{z}_d &= a^2 - b^2 + c^2 + d^2 + i \cdot (+2ab) + j \cdot (+2bd) + ij \cdot (-2ad) \\
 \bar{z}_{cd} * \bar{z}_c &= a^2 - b^2 - c^2 - d^2 + i \cdot (+2ab) + j \cdot (-2ac) + ij \cdot (-2bc) \\
 \bar{z}_{cd} * \bar{z}_{cd} &= a^2 - b^2 - c^2 + d^2 + i \cdot (+2(ab - cd)) + j \cdot (-2(ac - bd)) + ij \cdot (-2(ad + bc)) \\
 \bar{z}_{cd} * \bar{z}_b &= a^2 + b^2 + c^2 - d^2 + i \cdot (+2cd) + j \cdot (-2bd) + ij \cdot (+2bc) \\
 \bar{z}_{cd} * \bar{z}_{bd} &= a^2 + b^2 + c^2 + d^2 + ij \cdot (-2(ad - bc)) \\
 \bar{z}_{cd} * \bar{z}_{bc} &= a^2 + b^2 - c^2 - d^2 + j \cdot (-2(ac + bd)) \\
 \bar{z}_{cd} * \bar{z}_{bcd} &= a^2 + b^2 - c^2 + d^2 + i \cdot (-2cd) + j \cdot (-2ac) + ij \cdot (-2ad)
 \end{aligned}$$

$$\begin{aligned}
 \bar{z}_b * z &= a^2 + b^2 - c^2 + d^2 + i \cdot (-2cd) + j \cdot (+2ac) + ij \cdot (+2ad) \\
 \bar{z}_b * \bar{z}_d &= a^2 + b^2 - c^2 - d^2 + j \cdot (+2(ac - bd)) \\
 \bar{z}_b * \bar{z}_c &= a^2 + b^2 + c^2 + d^2 + ij \cdot (+2(ad + bc)) \\
 \bar{z}_b * \bar{z}_{cd} &= a^2 + b^2 + c^2 - d^2 + i \cdot (+2cd) + j \cdot (-2bd) + ij \cdot (+2bc) \\
 \bar{z}_b * \bar{z}_b &= a^2 - b^2 - c^2 + d^2 + i \cdot (-2(ab + cd)) + j \cdot (+2(ac + bd)) + ij \cdot (+2(ad - bc)) \\
 \bar{z}_b * \bar{z}_{bd} &= a^2 - b^2 - c^2 - d^2 + i \cdot (-2ab) + j \cdot (+2ac) + ij \cdot (-2bc) \\
 \bar{z}_b * \bar{z}_{bc} &= a^2 - b^2 + c^2 + d^2 + i \cdot (-2ab) + j \cdot (+2bd) + ij \cdot (+2ad) \\
 \bar{z}_b * \bar{z}_{bcd} &= a^2 - b^2 + c^2 - d^2 + i \cdot (-2(ab - cd))
 \end{aligned}$$

$$\begin{aligned}
\bar{z}_{bd} * z &= a^2 + b^2 - c^2 - d^2 + j \cdot (+2(ac + bd)) \\
\bar{z}_{bd} * \bar{z}_d &= a^2 + b^2 - c^2 + d^2 + i \cdot (+2cd) + j \cdot (+2ac) + ij \cdot (-2ad) \\
\bar{z}_{bd} * \bar{z}_c &= a^2 + b^2 + c^2 - d^2 + i \cdot (-2cd) + j \cdot (+2bd) + ij \cdot (+2bc) \\
\bar{z}_{bd} * \bar{z}_{cd} &= a^2 + b^2 + c^2 + d^2 + ij \cdot (-2(ad - bc)) \\
\bar{z}_{bd} * \bar{z}_b &= a^2 - b^2 - c^2 - d^2 + i \cdot (-2ab) + j \cdot (+2ac) + ij \cdot (-2bc) \\
\bar{z}_{bd} * \bar{z}_{bd} &= a^2 - b^2 - c^2 + d^2 + i \cdot (-2(ab - cd)) + j \cdot (+2(ac - bd)) + ij \cdot (-2(ad + bc)) \\
\bar{z}_{bd} * \bar{z}_{bc} &= a^2 - b^2 + c^2 - d^2 + i \cdot (-2(ab + cd)) \\
\bar{z}_{bd} * \bar{z}_{bcd} &= a^2 - b^2 + c^2 + d^2 + i \cdot (-2ab) + j \cdot (-2bd) + ij \cdot (-2ad)
\end{aligned}$$

$$\begin{aligned}
\bar{z}_{bc} * z &= a^2 + b^2 + c^2 + d^2 + ij \cdot (+2(ad - bc)) \\
\bar{z}_{bc} * \bar{z}_d &= a^2 + b^2 + c^2 - d^2 + i \cdot (-2cd) + j \cdot (-2bd) + ij \cdot (-2bc) \\
\bar{z}_{bc} * \bar{z}_c &= a^2 + b^2 - c^2 + d^2 + i \cdot (+2cd) + j \cdot (-2ac) + ij \cdot (+2ad) \\
\bar{z}_{bc} * \bar{z}_{cd} &= a^2 + b^2 - c^2 - d^2 + j \cdot (-2(ac + bd)) \\
\bar{z}_{bc} * \bar{z}_b &= a^2 - b^2 + c^2 + d^2 + i \cdot (-2ab) + j \cdot (+2bd) + ij \cdot (+2ad) \\
\bar{z}_{bc} * \bar{z}_{bd} &= a^2 - b^2 + c^2 - d^2 + i \cdot (-2(ab + cd)) \\
\bar{z}_{bc} * \bar{z}_{bc} &= a^2 - b^2 - c^2 + d^2 + i \cdot (-2(ab - cd)) + j \cdot (-2(ac - bd)) + ij \cdot (+2(ad + bc)) \\
\bar{z}_{bc} * \bar{z}_{bcd} &= a^2 - b^2 - c^2 - d^2 + i \cdot (-2ab) + j \cdot (-2ac) + ij \cdot (+2bc)
\end{aligned}$$

$$\begin{aligned}
\bar{z}_{bcd} * z &= a^2 + b^2 + c^2 - d^2 + i \cdot (+2cd) + j \cdot (+2bd) + ij \cdot (-2bc) \\
\bar{z}_{bcd} * \bar{z}_d &= a^2 + b^2 + c^2 + d^2 + ij \cdot (-2(ad + bc)) \\
\bar{z}_{bcd} * \bar{z}_c &= a^2 + b^2 - c^2 - d^2 + j \cdot (-2(ac - bd)) \\
\bar{z}_{bcd} * \bar{z}_{cd} &= a^2 + b^2 - c^2 + d^2 + i \cdot (-2cd) + j \cdot (-2ac) + ij \cdot (-2ad) \\
\bar{z}_{bcd} * \bar{z}_b &= a^2 - b^2 + c^2 - d^2 + i \cdot (-2(ab - cd)) \\
\bar{z}_{bcd} * \bar{z}_{bd} &= a^2 - b^2 + c^2 + d^2 + i \cdot (-2ab) + j \cdot (-2bd) + ij \cdot (-2ad) \\
\bar{z}_{bcd} * \bar{z}_{bc} &= a^2 - b^2 - c^2 - d^2 + i \cdot (-2ab) + j \cdot (-2ac) + ij \cdot (+2bc) \\
\bar{z}_{bcd} * \bar{z}_{bcd} &= a^2 - b^2 - c^2 + d^2 + i \cdot (-2(ab + cd)) + j \cdot (-2(ac + bd)) + ij \cdot (-2(ad - bc))
\end{aligned}$$

10.3

$$\begin{aligned}
z * \bar{z}_{bc} &= a^2 + b^2 + c^2 + d^2 + ij \cdot (+2(ad - bc)) \\
\bar{z}_d * \bar{z}_{bcd} &= a^2 + b^2 + c^2 + d^2 + ij \cdot (-2(ad + bc)) \\
\bar{z}_c * \bar{z}_b &= a^2 + b^2 + c^2 + d^2 + ij \cdot (+2(ad + bc)) \\
\bar{z}_{cd} * \bar{z}_{bd} &= a^2 + b^2 + c^2 + d^2 + ij \cdot (-2(ad - bc)) \\
\bar{z}_b * \bar{z}_c &\doteq a^2 + b^2 + c^2 + d^2 + ij \cdot (+2(ad + bc)) \\
\bar{z}_{bd} * \bar{z}_{cd} &\doteq a^2 + b^2 + c^2 + d^2 + ij \cdot (-2(ad - bc)) \\
\bar{z}_{bc} * z &\doteq a^2 + b^2 + c^2 + d^2 + ij \cdot (+2(ad - bc)) \\
\bar{z}_{bcd} * \bar{z}_d &\doteq a^2 + b^2 + c^2 + d^2 + ij \cdot (-2(ad + bc))
\end{aligned}$$

$$\begin{aligned}
z * \bar{z}_{bcd} &= a^2 + b^2 + c^2 - d^2 + i \cdot (+2cd) + j \cdot (+2bd) + ij \cdot (-2bc) \\
\bar{z}_d * \bar{z}_{bc} &= a^2 + b^2 + c^2 - d^2 + i \cdot (-2cd) + j \cdot (-2bd) + ij \cdot (-2bc) \\
\bar{z}_c * \bar{z}_{bd} &= a^2 + b^2 + c^2 - d^2 + i \cdot (-2cd) + j \cdot (+2bd) + ij \cdot (+2bc) \\
\bar{z}_{cd} * \bar{z}_b &= a^2 + b^2 + c^2 - d^2 + i \cdot (+2cd) + j \cdot (-2bd) + ij \cdot (+2bc) \\
\bar{z}_b * \bar{z}_{cd} &\doteq a^2 + b^2 + c^2 - d^2 + i \cdot (+2cd) + j \cdot (-2bd) + ij \cdot (+2bc) \\
\bar{z}_{bd} * \bar{z}_c &\doteq a^2 + b^2 + c^2 - d^2 + i \cdot (-2cd) + j \cdot (+2bd) + ij \cdot (+2bc) \\
\bar{z}_{bc} * \bar{z}_d &\doteq a^2 + b^2 + c^2 - d^2 + i \cdot (-2cd) + j \cdot (-2bd) + ij \cdot (-2bc) \\
\bar{z}_{bcd} * z &\doteq a^2 + b^2 + c^2 - d^2 + i \cdot (+2cd) + j \cdot (+2bd) + ij \cdot (-2bc)
\end{aligned}$$

$$\begin{aligned}
z * \bar{z}_b &= a^2 + b^2 - c^2 + d^2 + i \cdot (-2cd) + j \cdot (+2ac) + ij \cdot (+2ad) \\
\bar{z}_d * \bar{z}_{bd} &= a^2 + b^2 - c^2 + d^2 + i \cdot (+2cd) + j \cdot (+2ac) + ij \cdot (-2ad) \\
\bar{z}_c * \bar{z}_{bc} &= a^2 + b^2 - c^2 + d^2 + i \cdot (+2cd) + j \cdot (-2ac) + ij \cdot (+2ad) \\
\bar{z}_{cd} * \bar{z}_{bcd} &= a^2 + b^2 - c^2 + d^2 + i \cdot (-2cd) + j \cdot (-2ac) + ij \cdot (-2ad) \\
\bar{z}_b * z &\doteq a^2 + b^2 - c^2 + d^2 + i \cdot (-2cd) + j \cdot (+2ac) + ij \cdot (+2ad) \\
\bar{z}_{bd} * \bar{z}_d &\doteq a^2 + b^2 - c^2 + d^2 + i \cdot (+2cd) + j \cdot (+2ac) + ij \cdot (-2ad) \\
\bar{z}_{bc} * \bar{z}_c &\doteq a^2 + b^2 - c^2 + d^2 + i \cdot (+2cd) + j \cdot (-2ac) + ij \cdot (+2ad) \\
\bar{z}_{bcd} * \bar{z}_{cd} &\doteq a^2 + b^2 - c^2 + d^2 + i \cdot (-2cd) + j \cdot (-2ac) + ij \cdot (-2ad)
\end{aligned}$$

$$\begin{aligned}
z * \bar{z}_{bd} &= a^2 + b^2 - c^2 - d^2 + j \cdot (+2(ac + bd)) \\
\bar{z}_d * \bar{z}_b &= a^2 + b^2 - c^2 - d^2 + j \cdot (+2(ac - bd)) \\
\bar{z}_c * \bar{z}_{bcd} &= a^2 + b^2 - c^2 - d^2 + j \cdot (-2(ac - bd)) \\
\bar{z}_{cd} * \bar{z}_{bc} &= a^2 + b^2 - c^2 - d^2 + j \cdot (-2(ac + bd)) \\
\bar{z}_b * \bar{z}_d &\doteq a^2 + b^2 - c^2 - d^2 + j \cdot (+2(ac - bd)) \\
\bar{z}_{bd} * z &\doteq a^2 + b^2 - c^2 - d^2 + j \cdot (+2(ac + bd)) \\
\bar{z}_{bc} * \bar{z}_{cd} &\doteq a^2 + b^2 - c^2 - d^2 + j \cdot (-2(ac + bd)) \\
\bar{z}_{bcd} * \bar{z}_c &\doteq a^2 + b^2 - c^2 - d^2 + j \cdot (-2(ac - bd))
\end{aligned}$$

$$\begin{aligned}
z * \bar{z}_c &= a^2 - b^2 + c^2 + d^2 + i \cdot (+2ab) + j \cdot (-2bd) + ij \cdot (+2ad) \\
\bar{z}_d * \bar{z}_{cd} &= a^2 - b^2 + c^2 + d^2 + i \cdot (+2ab) + j \cdot (+2bd) + ij \cdot (-2ad) \\
\bar{z}_c * z &\doteq a^2 - b^2 + c^2 + d^2 + i \cdot (+2ab) + j \cdot (-2bd) + ij \cdot (+2ad) \\
\bar{z}_{cd} * \bar{z}_d &\doteq a^2 - b^2 + c^2 + d^2 + i \cdot (+2ab) + j \cdot (+2bd) + ij \cdot (-2ad) \\
\bar{z}_b * \bar{z}_{bc} &= a^2 - b^2 + c^2 + d^2 + i \cdot (-2ab) + j \cdot (+2bd) + ij \cdot (+2ad) \\
\bar{z}_{bd} * \bar{z}_{bcd} &= a^2 - b^2 + c^2 + d^2 + i \cdot (-2ab) + j \cdot (-2bd) + ij \cdot (-2ad) \\
\bar{z}_{bc} * \bar{z}_b &\doteq a^2 - b^2 + c^2 + d^2 + i \cdot (-2ab) + j \cdot (+2bd) + ij \cdot (+2ad) \\
\bar{z}_{bcd} * \bar{z}_{bd} &\doteq a^2 - b^2 + c^2 + d^2 + i \cdot (-2ab) + j \cdot (-2bd) + ij \cdot (-2ad)
\end{aligned}$$

$$\begin{aligned}
z * \bar{z}_{cd} &= a^2 - b^2 + c^2 - d^2 + i \cdot (+2(ab + cd)) \\
\bar{z}_d * \bar{z}_c &= a^2 - b^2 + c^2 - d^2 + i \cdot (+2(ab - cd)) \\
\bar{z}_c * \bar{z}_d &\doteq a^2 - b^2 + c^2 - d^2 + i \cdot (+2(ab - cd)) \\
\bar{z}_{cd} * z &\doteq a^2 - b^2 + c^2 - d^2 + i \cdot (+2(ab + cd)) \\
\bar{z}_b * \bar{z}_{bcd} &= a^2 - b^2 + c^2 - d^2 + i \cdot (-2(ab - cd)) \\
\bar{z}_{bd} * \bar{z}_{bc} &= a^2 - b^2 + c^2 - d^2 + i \cdot (-2(ab + cd)) \\
\bar{z}_{bc} * \bar{z}_{bd} &\doteq a^2 - b^2 + c^2 - d^2 + i \cdot (-2(ab + cd)) \\
\bar{z}_{bcd} * \bar{z}_b &\doteq a^2 - b^2 + c^2 - d^2 + i \cdot (-2(ab - cd))
\end{aligned}$$

$$\begin{aligned}
z * z &= a^2 - b^2 - c^2 + d^2 + i \cdot (+2(ab - cd)) + j \cdot (+2(ac - bd)) + ij \cdot (+2(ad + bc)) \\
\bar{z}_d * \bar{z}_d &= a^2 - b^2 - c^2 + d^2 + i \cdot (+2(ab + cd)) + j \cdot (+2(ac + bd)) + ij \cdot (-2(ad - bc)) \\
\bar{z}_c * \bar{z}_c &= a^2 - b^2 - c^2 + d^2 + i \cdot (+2(ab + cd)) + j \cdot (-2(ac + bd)) + ij \cdot (+2(ad - bc)) \\
\bar{z}_{cd} * \bar{z}_{cd} &= a^2 - b^2 - c^2 + d^2 + i \cdot (+2(ab - cd)) + j \cdot (-2(ac - bd)) + ij \cdot (-2(ad + bc)) \\
\bar{z}_b * \bar{z}_b &= a^2 - b^2 - c^2 + d^2 + i \cdot (-2(ab + cd)) + j \cdot (+2(ac + bd)) + ij \cdot (+2(ad - bc)) \\
\bar{z}_{bd} * \bar{z}_{bd} &= a^2 - b^2 - c^2 + d^2 + i \cdot (-2(ab - cd)) + j \cdot (+2(ac - bd)) + ij \cdot (-2(ad + bc)) \\
\bar{z}_{bc} * \bar{z}_{bc} &= a^2 - b^2 - c^2 + d^2 + i \cdot (-2(ab - cd)) + j \cdot (-2(ac - bd)) + ij \cdot (+2(ad + bc)) \\
\bar{z}_{bcd} * \bar{z}_{bcd} &= a^2 - b^2 - c^2 + d^2 + i \cdot (-2(ab + cd)) + j \cdot (-2(ac + bd)) + ij \cdot (-2(ad - bc))
\end{aligned}$$

$$\begin{aligned}
z * \bar{z}_d &= a^2 - b^2 - c^2 - d^2 + i \cdot (+2ab) + j \cdot (+2ac) + ij \cdot (+2bc) \\
\bar{z}_d * z &\doteq a^2 - b^2 - c^2 - d^2 + i \cdot (+2ab) + j \cdot (+2ac) + ij \cdot (+2bc) \\
\bar{z}_c * \bar{z}_{cd} &= a^2 - b^2 - c^2 - d^2 + i \cdot (+2ab) + j \cdot (-2ac) + ij \cdot (-2bc) \\
\bar{z}_{cd} * \bar{z}_c &\doteq a^2 - b^2 - c^2 - d^2 + i \cdot (+2ab) + j \cdot (-2ac) + ij \cdot (-2bc) \\
\bar{z}_b * \bar{z}_{bd} &= a^2 - b^2 - c^2 - d^2 + i \cdot (-2ab) + j \cdot (+2ac) + ij \cdot (-2bc) \\
\bar{z}_{bd} * \bar{z}_b &\doteq a^2 - b^2 - c^2 - d^2 + i \cdot (-2ab) + j \cdot (+2ac) + ij \cdot (-2bc) \\
\bar{z}_{bc} * \bar{z}_{bcd} &= a^2 - b^2 - c^2 - d^2 + i \cdot (-2ab) + j \cdot (-2ac) + ij \cdot (+2bc) \\
\bar{z}_{bcd} * \bar{z}_{bc} &\doteq a^2 - b^2 - c^2 - d^2 + i \cdot (-2ab) + j \cdot (-2ac) + ij \cdot (+2bc)
\end{aligned}$$

10.4

$$\begin{aligned}
a^2 + b^2 + c^2 + d^2 &= 1/2 \cdot (z * \bar{z}_{bc} + \bar{z}_{bd} * \bar{z}_{cd}) \\
a^2 + b^2 + c^2 + d^2 &= 1/2 \cdot (\bar{z}_b * \bar{z}_c + \bar{z}_d * \bar{z}_{bcd}) \\
a^2 + b^2 + c^2 - d^2 &= 1/4 \cdot (z * \bar{z}_{bcd} + \bar{z}_b * \bar{z}_{cd} + \bar{z}_c * \bar{z}_{bd} + \bar{z}_d * \bar{z}_{bc}) \\
a^2 + b^2 - c^2 + d^2 &= 1/4 \cdot (z * \bar{z}_b + \bar{z}_c * \bar{z}_{bc} + \bar{z}_d * \bar{z}_{bd} + \bar{z}_{cd} * \bar{z}_{bcd}) \\
a^2 + b^2 - c^2 - d^2 &= 1/2 \cdot (z * \bar{z}_{bd} + \bar{z}_{bc} * \bar{z}_{cd}) \\
a^2 + b^2 - c^2 - d^2 &= 1/2 \cdot (\bar{z}_b * \bar{z}_d + \bar{z}_c * \bar{z}_{bcd}) \\
a^2 - b^2 + c^2 + d^2 &= 1/4 \cdot (z * \bar{z}_c + \bar{z}_b * \bar{z}_{bc} + \bar{z}_d * \bar{z}_{cd} + \bar{z}_{bd} * \bar{z}_{bcd}) \\
a^2 - b^2 + c^2 - d^2 &= 1/2 \cdot (z * \bar{z}_{cd} + \bar{z}_{bc} * \bar{z}_{bd}) \\
a^2 - b^2 + c^2 - d^2 &= 1/2 \cdot (\bar{z}_b * \bar{z}_{bcd} + \bar{z}_c * \bar{z}_d) \\
a^2 - b^2 - c^2 + d^2 &= 1/4 \cdot (z * z + \bar{z}_{bc} * \bar{z}_{bc} + \bar{z}_{bd} * \bar{z}_{bd} + \bar{z}_{cd} * \bar{z}_{cd}) \\
a^2 - b^2 - c^2 + d^2 &= 1/4 \cdot (\bar{z}_b * \bar{z}_b + \bar{z}_c * \bar{z}_c + \bar{z}_d * \bar{z}_d + \bar{z}_{bcd} * \bar{z}_{bcd}) \\
a^2 - b^2 - c^2 - d^2 &= 1/4 \cdot (z * \bar{z}_d + \bar{z}_b * \bar{z}_{bd} + \bar{z}_c * \bar{z}_{cd} + \bar{z}_{bc} * \bar{z}_{bcd})
\end{aligned}$$

11 Exponential form

$$z = (a + ib) + j \cdot (c + id) = r * e^{i\phi} + j \cdot \rho * e^{i\psi}$$

$$z = |z| * e^{i\alpha + j\beta + ij\gamma} = R * e^{i\alpha + j\beta + ij\gamma}$$

$$e^{i\alpha} = \cos \alpha + i \sin \alpha$$

$$e^{j\beta} = \cos \beta + j \sin \beta$$

$$e^{ij\gamma} = \cosh \gamma + ij \sinh \gamma$$

$$|e^{i\phi}| = |e^{j\phi}| = |e^{ij\phi}| = 1$$

$$i = e^{i\pi/2}$$

$$j = e^{j\pi/2}$$

$$ij = e^{(i+j)\pi/2}$$

$$\sinh \gamma + ij \cosh \gamma = ij \cdot (\cosh \gamma + ij \sinh \gamma) = ij \cdot e^{ij\gamma}$$

$$\sinh \gamma + ij \cosh \gamma = e^{(i+j)\pi/2 + ij\gamma}$$

$$z = R * (\cos \alpha + i \sin \alpha) (\cos \beta + j \sin \beta) (\cosh \gamma + ij \sinh \gamma)$$

$$z = R * (\cos \alpha \cos \beta + i \sin \alpha \cos \beta + j \cos \alpha \sin \beta + ij \sin \alpha \sin \beta) (\cosh \gamma + ij \sinh \gamma)$$

$$a = R * (\cosh \gamma \cos \alpha \cos \beta + \sinh \gamma \sin \alpha \sin \beta)$$

$$b = R * (\cosh \gamma \sin \alpha \cos \beta - \sinh \gamma \cos \alpha \sin \beta)$$

$$c = R * (\cosh \gamma \cos \alpha \sin \beta - \sinh \gamma \sin \alpha \cos \beta)$$

$$d = R * (\cosh \gamma \sin \alpha \sin \beta + \sinh \gamma \cos \alpha \cos \beta)$$

$$\begin{cases} a + d = R * e^{+\gamma} * \cos(\alpha - \beta) \\ b - c = R * e^{+\gamma} * \sin(\alpha - \beta) \\ a - d = R * e^{-\gamma} * \cos(\alpha + \beta) \\ b + c = R * e^{-\gamma} * \sin(\alpha + \beta) \end{cases}$$

$$\begin{cases} (a + d)^2 + (b - c)^2 = R^2 * e^{2\gamma} \\ (a - d)^2 + (b + c)^2 = R^2 * e^{-2\gamma} \end{cases}$$

$$\begin{cases} a^2 + b^2 + c^2 + d^2 = R^2 * \cosh 2\gamma \\ 2(ad - bc) = R^2 * \sinh 2\gamma \end{cases}$$

$$\begin{cases} \tan(\alpha - \beta) = \frac{b - c}{a + d} = \arg(a + d, b - c) \\ \tan(\alpha + \beta) = \frac{b + c}{a - d} = \arg(a - d, b + c) \end{cases}$$

$$R = \sqrt[4]{\left((a + d)^2 + (b - c)^2 \right) * \left((a - d)^2 + (b + c)^2 \right)}$$

$$R = \sqrt[4]{(r^2 + \rho^2)^2 - 4r^2\rho^2 * \sin^2(\psi - \phi)}$$

$$R = \sqrt[4]{r^4 + \rho^4 + 2r^2\rho^2 * \cos 2(\psi - \phi)}$$

$$\gamma = \frac{1}{4} \ln \frac{(a + d)^2 + (b - c)^2}{(a - d)^2 + (b + c)^2}$$

$$\gamma = \frac{1}{4} \ln \frac{r^2 + \rho^2 + 2r\rho * \sin(\psi - \phi)}{r^2 + \rho^2 - 2r\rho * \sin(\psi - \phi)}$$

$$\alpha = \frac{1}{2} [\arg(a + d, b - c) + \arg(a - d, b + c)]$$

$$\beta = \frac{1}{2} [\arg(a - d, b + c) - \arg(a + d, b - c)]$$

$$\arg(x, y) = \arctan(y, x) = \arctan(y : x) = \arctan(y/x)$$

11.1

$$R^2 = r^2 + \rho^2 - 2r\rho \cdot \cos \theta, \quad \cos \theta = ?$$

$$\cos \theta = \frac{1}{2r\rho} * (r^2 + \rho^2 - R^2)$$

$$\cos \theta = \frac{1}{2r\rho} * \left(r^2 + \rho^2 - \sqrt{(r^2 + \rho^2)^2 - 4r^2\rho^2 * \sin^2(\psi - \phi)} \right)$$

$$\cos \theta = \frac{r^2 + \rho^2}{2r\rho} - \sqrt{\left(\frac{r^2 + \rho^2}{2r\rho} \right)^2 - \sin^2(\psi - \phi)}$$

$$\frac{r^2 + \rho^2}{2r\rho} - 1 = \frac{r^2 + \rho^2 - 2r\rho}{2r\rho} = \frac{(r - \rho)^2}{2r\rho} \geq 0, \quad \frac{r^2 + \rho^2}{2r\rho} \geq 1$$

$$(\cos \theta)_{\min} = 0$$

$$(\cos \theta)_{\max} = \frac{r^2 + \rho^2}{2r\rho} - \sqrt{\left(\frac{r^2 + \rho^2}{2r\rho} \right)^2 - 1} = \frac{1}{2r\rho} * \left(r^2 + \rho^2 - (r + \rho) \cdot |r - \rho| \right)$$

$$(\cos \theta)_{\max} = \frac{\rho}{r}, \quad r > \rho$$

$$(\cos \theta)_{\max} = \frac{r}{\rho}, \quad \rho > r$$

11.2

$$\begin{cases} e^{+\gamma} = \sqrt[4]{\frac{(a+d)^2 + (b-c)^2}{(a-d)^2 + (b+c)^2}} \\ e^{-\gamma} = \sqrt[4]{\frac{(a-d)^2 + (b+c)^2}{(a+d)^2 + (b-c)^2}} \end{cases}$$

$$\begin{cases} R * e^{+\gamma} = \sqrt{(a+d)^2 + (b-c)^2} \\ R * e^{-\gamma} = \sqrt{(a-d)^2 + (b+c)^2} \end{cases}$$

$$\begin{cases} \alpha - \beta = \arg(a+d, b-c) \\ \alpha + \beta = \arg(a-d, b+c) \end{cases}$$

11.3

$$\gamma = 0 \Rightarrow$$

$$a \cdot d = b \cdot c$$

$$R^2 = a^2 + b^2 + c^2 + d^2$$

$$R^2 = (a+d)^2 + (b-c)^2$$

$$R^2 = (a-d)^2 + (b+c)^2$$

11.4

$$\phi = \psi \Rightarrow$$

$$z = (a+ib) \cdot (c+jd) = ac + i \cdot bc + j \cdot ad + ij \cdot bd = \underline{a} + i \cdot \underline{b} + j \cdot \underline{c} + ij \cdot \underline{d}$$

$$\underline{a} = a \cdot c$$

$$\underline{b} = b \cdot c$$

$$\underline{c} = a \cdot d$$

$$\underline{d} = b \cdot d$$

$$\underline{a} \cdot \underline{d} = \underline{b} \cdot \underline{c} = a \cdot b \cdot c \cdot d$$

$$R^2 = \underline{a}^2 + \underline{b}^2 + \underline{c}^2 + \underline{d}^2$$

$$\gamma = 0$$

11.5 $\mathbf{R=0}$

$$z = (a + ib) + j(c + id) = a + ib + jc + ijd = R * e^{i\alpha + j\beta + ij\gamma}$$

$$R = \sqrt[4]{\left((a+d)^2 + (b-c)^2\right) * \left((a-d)^2 + (b+c)^2\right)}$$

$$R = 0$$

$$z = (0) * e^{j\theta}$$

$$1) a = d \neq 0 \wedge b = -c \neq 0$$

$$z = a(1 + ij) + b(i - j) = a + ib - jb + ija = (a + ib) + j(-b + ia) = (a + ib) + j(i(a + ib))$$

$$\theta = \arctan(+i)$$

$$2) a = -d \neq 0 \wedge b = c \neq 0$$

$$z = a(1 - ij) + b(i + j) = a + ib + jb - ija = (a + ib) + j(b - ia) = (a + ib) + j(-i(a + ib))$$

$$\theta = \arctan(-i)$$

$$3) a = d = 0 \wedge b = c \neq 0$$

$$z = b(i + j) = ib + jb = (ib) + j(b)$$

$$\theta = \arctan(-i)$$

$$4) a = d = 0 \wedge b = -c \neq 0$$

$$z = b(i - j) = ib - jb = (ib) + j(-b)$$

$$\theta = \arctan(+i)$$

$$5) b = c = 0 \wedge a = d \neq 0$$

$$z = a(1 + ij) = a + ija = (a) + j(ia)$$

$$\theta = \arctan(+i)$$

$$6) b = c = 0 \wedge a = -d \neq 0$$

$$z = a(1 - ij) = a - ija = (a) + j(-ia)$$

$$\theta = \arctan(-i)$$

$$7) a = b = c = d = 0$$

$$z = 0$$

$$\arctan(+i) = +i \cdot \infty$$

$$\arctan(-i) = -i \cdot \infty$$

$$(1 + ij) * (1 + ij) = 1 + ij + ij + 1 = 2 \cdot (1 + ij)$$

$$(1 + ij) * (i - j) = i - j - j + i = 2 \cdot (i - j)$$

$$(1 + ij) * (1 - ij) = 1 - ij + ij - 1 = 0$$

$$(1 + ij) * (i + j) = i + j - j - i = 0$$

$$(i - j) * (1 + ij) = i - j - j + i = 2 \cdot (i - j)$$

$$(i - j) * (i - j) = -1 - ij - ij - 1 = -2 \cdot (1 + ij)$$

$$(i - j) * (1 - ij) = i + j - j - i = 0$$

$$(i - j) * (i + j) = -1 + ij - ij + 1 = 0$$

$$(1 - ij) * (1 + ij) = 1 + ij - ij - 1 = 0$$

$$(1 - ij) * (i - j) = i - j + j - i = 0$$

$$(1 - ij) * (1 - ij) = 1 - ij - ij + 1 = 2 \cdot (1 - ij)$$

$$(1 - ij) * (i + j) = i + j + j + i = 2 \cdot (i + j)$$

$$(i + j) * (1 + ij) = i - j + j - i = 0$$

$$(i + j) * (i - j) = -1 - ij + ij + 1 = 0$$

$$(i + j) * (1 - ij) = i + j + j + i = 2 \cdot (i + j)$$

$$(i + j) * (i + j) = -1 + ij + ij - 1 = -2 \cdot (1 - ij)$$

12 Conjugate \pm

12.1 e+

$$z = e^{i\alpha+j\beta+ij\gamma} = (a + ib) + j(c + id)$$

$$\begin{aligned} z &= (\cos \alpha + i \sin \alpha) (\cos \beta + j \sin \beta) (\cosh \gamma + ij \sinh \gamma) \\ z &= (\cos \alpha \cos \beta + i \sin \alpha \cos \beta + j \cos \alpha \sin \beta + ij \sin \alpha \sin \beta) (\cosh \gamma + ij \sinh \gamma) \end{aligned}$$

$$\begin{aligned} a &= \cosh \gamma \cos \alpha \cos \beta + \sinh \gamma \sin \alpha \sin \beta \\ b &= \cosh \gamma \sin \alpha \cos \beta - \sinh \gamma \cos \alpha \sin \beta \\ c &= \cosh \gamma \cos \alpha \sin \beta - \sinh \gamma \sin \alpha \cos \beta \\ d &= \cosh \gamma \sin \alpha \sin \beta + \sinh \gamma \cos \alpha \cos \beta \end{aligned}$$

$$\begin{cases} a + d = e^{+\gamma} * \cos(\alpha - \beta) \\ b - c = e^{+\gamma} * \sin(\alpha - \beta) \\ a - d = e^{-\gamma} * \cos(\alpha + \beta) \\ b + c = e^{-\gamma} * \sin(\alpha + \beta) \end{cases}$$

$$\begin{cases} (a + d)^2 + (b - c)^2 = e^{2\gamma} \\ (a - d)^2 + (b + c)^2 = e^{-2\gamma} \end{cases}$$

$$\begin{cases} V = a^2 + b^2 + c^2 + d^2 = \cosh 2\gamma \\ U = 2(ad - bc) = \sinh 2\gamma \\ V^2 - U^2 = 1 \end{cases}$$

12.2 e-

$$\bar{z} = e^{-i\alpha-j\beta-ij\gamma} = (\underline{a} + i\underline{b}) + j(\underline{c} + i\underline{d})$$

$$\begin{aligned} \bar{z} &= (\cos \alpha - i \sin \alpha) (\cos \beta - j \sin \beta) (\cosh \gamma - ij \sinh \gamma) \\ \bar{z} &= (\cos \alpha \cos \beta - i \sin \alpha \cos \beta - j \cos \alpha \sin \beta + ij \sin \alpha \sin \beta) (\cosh \gamma - ij \sinh \gamma) \end{aligned}$$

$$\begin{cases} \underline{a} = \cosh \gamma \cos \alpha \cos \beta - \sinh \gamma \sin \alpha \sin \beta \\ \underline{b} = -\cosh \gamma \sin \alpha \cos \beta - \sinh \gamma \cos \alpha \sin \beta \\ \underline{c} = -\cosh \gamma \cos \alpha \sin \beta - \sinh \gamma \sin \alpha \cos \beta \\ \underline{d} = \cosh \gamma \sin \alpha \sin \beta - \sinh \gamma \cos \alpha \cos \beta \end{cases}$$

$$\begin{cases} \underline{a} + \underline{d} = e^{-\gamma} * \cos(\alpha - \beta) \\ \underline{b} - \underline{c} = -e^{-\gamma} * \sin(\alpha - \beta) \\ \underline{a} - \underline{d} = e^{+\gamma} * \cos(\alpha + \beta) \\ \underline{b} + \underline{c} = -e^{+\gamma} * \sin(\alpha + \beta) \end{cases}$$

$$\begin{cases} (\underline{a} + \underline{d})^2 + (\underline{b} - \underline{c})^2 = e^{-2\gamma} \\ (\underline{a} - \underline{d})^2 + (\underline{b} + \underline{c})^2 = e^{2\gamma} \end{cases}$$

$$\begin{cases} \underline{V} = \underline{a}^2 + \underline{b}^2 + \underline{c}^2 + \underline{d}^2 = \cosh 2\gamma \\ \underline{U} = 2(\underline{a}\underline{d} - \underline{b}\underline{c}) = -\sinh 2\gamma \\ \underline{V}^2 - \underline{U}^2 = 1 \end{cases}$$

$$\underline{a} = aV - dU$$

$$\underline{b} = -bV - cU$$

$$\underline{c} = -bU - cV$$

$$\underline{d} = -aU + dV$$

13 Exponentiation

$$\begin{aligned}
 z &= (a + ib) + j(c + id) \\
 &= R * e^{i\alpha + j\beta + ij\gamma} \\
 &= R * e^{i(\alpha + \pi \cdot k + 2\pi \cdot m)} * e^{j(\beta + \pi \cdot k + 2\pi \cdot p)} * e^{ij\gamma} \\
 &= R * e^{i\alpha} * e^{j\beta} * e^{ij\gamma} * e^{(\pi \cdot k + 2\pi \cdot m)} * e^{(\pi \cdot k + 2\pi \cdot p)}
 \end{aligned}$$

$$\begin{aligned}
 e^{i(\alpha) + j(\beta)} &= e^{i(\alpha + \pi) + j(\beta + \pi)} \\
 &= e^{i(\alpha + \pi) + j(\beta - \pi)} \\
 &= e^{i(\alpha - \pi) + j(\beta + \pi)} \\
 &= e^{i(\alpha - \pi) + j(\beta - \pi)}
 \end{aligned}$$

13.1 z^n

$$z^n = R^n * e^{i(\alpha \cdot n)} * e^{j(\beta \cdot n)} * e^{ij(\gamma \cdot n)}$$

13.2 $\sqrt[n]{z}$

$$\begin{aligned}
 \sqrt[n]{z} &= \sqrt[n]{R} * e^{i(\alpha/n)} * e^{j(\beta/n)} * e^{ij(\gamma/n)} * e^{i(\pi \cdot k + 2\pi \cdot m)/n} * e^{j(\pi \cdot k + 2\pi \cdot p)/n} \\
 k &= 0, 1 \\
 m &= 0, 1, \dots, n - 1 \\
 p &= 0, 1, \dots, n - 1
 \end{aligned}$$

$$\begin{aligned}
 (\sqrt[n]{z})_{\langle 0|0|0 \rangle} &= \sqrt[n]{R} * e^{i(\alpha/n)} * e^{j(\beta/n)} * e^{ij(\gamma/n)} \\
 (\sqrt[n]{z})_{\langle 0|m|p \rangle} &= \sqrt[n]{R} * e^{i(\alpha + 2\pi \cdot m)/n} * e^{j(\beta + 2\pi \cdot p)/n} * e^{ij(\gamma/n)} \\
 (\sqrt[n]{z})_{\langle 1|m|p \rangle} &= \sqrt[n]{R} * e^{i(\alpha + \pi + 2\pi \cdot m)/n} * e^{j(\beta + \pi + 2\pi \cdot p)/n} * e^{ij(\gamma/n)}
 \end{aligned}$$

13.2.1 \sqrt{z}

$$n = 2$$

$$\begin{aligned}
 \sqrt{z} &= (\sqrt{R} * e^{i(\alpha/2)} * e^{j(\beta/2)} * e^{ij(\gamma/2)}) * e^{i(\pi \cdot k + 2\pi \cdot m)/2} * e^{j(\pi \cdot k + 2\pi \cdot p)/2} \\
 &= R' * e^{i(\pi \cdot k + 2\pi \cdot m)/2} * e^{j(\pi \cdot k + 2\pi \cdot p)/2}
 \end{aligned}$$

$$\begin{aligned}
 (\sqrt{z})_{\langle 0|0|0 \rangle} &= R' \\
 (\sqrt{z})_{\langle 0|1|0 \rangle} &= R' * e^{i(\pi)} = R' * (-1) \\
 (\sqrt{z})_{\langle 0|0|1 \rangle} &\doteq R' * e^{j(\pi)} = R' * (-1) \\
 (\sqrt{z})_{\langle 0|1|1 \rangle} &\doteq R' * e^{i(\pi)} * e^{j(\pi)} = R' \\
 (\sqrt{z})_{\langle 1|0|0 \rangle} &= R' * e^{i(\pi/2)} * e^{j(\pi/2)} = R' * (ij) \\
 (\sqrt{z})_{\langle 1|1|0 \rangle} &= R' * e^{i(\pi/2 + \pi)} * e^{j(\pi/2)} = R' * (-1) * e^{i(\pi/2)} * e^{j(\pi/2)} = R' * (-ij) \\
 (\sqrt{z})_{\langle 1|0|1 \rangle} &\doteq R' * e^{i(\pi/2)} * e^{j(\pi/2 + \pi)} = R' * (-1) * e^{i(\pi/2)} * e^{j(\pi/2)} = R' * (-ij) \\
 (\sqrt{z})_{\langle 1|1|1 \rangle} &\doteq R' * e^{i(\pi/2 + \pi)} * e^{j(\pi/2 + \pi)} = R' * e^{i(\pi/2)} * e^{j(\pi/2)} = R' * (ij)
 \end{aligned}$$

$$(\sqrt{z}) = R' * (\pm 1)$$

$$(\sqrt{z}) = R' * (\pm ij)$$

$$\begin{aligned}
 (\sqrt{z})_{\langle 0|0|0 \rangle} &= \sqrt{R} * e^{i(\alpha/2)} * e^{j(\beta/2)} * e^{ij(\gamma/2)} \\
 (\sqrt{z})_{\langle 0|1|0 \rangle} &= -\sqrt{R} * e^{i(\alpha/2)} * e^{j(\beta/2)} * e^{ij(\gamma/2)} \\
 (\sqrt{z})_{\langle 1|0|0 \rangle} &= \sqrt{R} * e^{i(\alpha/2 + \pi/2)} * e^{j(\beta/2 + \pi/2)} * e^{ij(\gamma/2)} \\
 (\sqrt{z})_{\langle 1|1|0 \rangle} &= -\sqrt{R} * e^{i(\alpha/2 + \pi/2)} * e^{j(\beta/2 + \pi/2)} * e^{ij(\gamma/2)}
 \end{aligned}$$

$$(\sqrt{1})_{\langle 0|0|0 \rangle} = 1$$

$$(\sqrt{1})_{\langle 0|1|0 \rangle} = -1$$

$$(\sqrt{1})_{\langle 1|0|0 \rangle} = ij$$

$$(\sqrt{1})_{\langle 1|1|0 \rangle} = -ij$$

$$\begin{aligned}
 (\sqrt{i})_{\langle 0|0|0 \rangle} &= e^{i(\pi/4)} & (\sqrt{j})_{\langle 0|0|0 \rangle} &= e^{j(\pi/4)} \\
 (\sqrt{i})_{\langle 0|1|0 \rangle} &= -e^{i(\pi/4)} & (\sqrt{j})_{\langle 0|1|0 \rangle} &= -e^{j(\pi/4)} \\
 (\sqrt{i})_{\langle 1|0|0 \rangle} &= -e^{i(-\pi/4)} * e^{j(\pi/2)} & (\sqrt{j})_{\langle 1|0|0 \rangle} &= -e^{i(\pi/2)} * e^{j(-\pi/4)} \\
 (\sqrt{i})_{\langle 1|1|0 \rangle} &= e^{i(-\pi/4)} * e^{j(\pi/2)} & (\sqrt{j})_{\langle 1|1|0 \rangle} &= e^{i(\pi/2)} * e^{j(-\pi/4)}
 \end{aligned}$$

$$\begin{aligned}
(\sqrt{i\bar{j}})\langle 0|0|0\rangle &= e^{i(\pi/4)} * e^{j(\pi/4)} \\
(\sqrt{i\bar{j}})\langle 0|1|0\rangle &= -e^{i(\pi/4)} * e^{j(\pi/4)} \\
(\sqrt{i\bar{j}})\langle 1|0|0\rangle &= e^{i(-\pi/4)} * e^{j(-\pi/4)} \\
(\sqrt{i\bar{j}})\langle 1|1|0\rangle &= -e^{i(-\pi/4)} * e^{j(-\pi/4)}
\end{aligned}$$

13.2.2 $\sqrt[3]{z}$

$$n = 3$$

$$\begin{aligned}
\sqrt[3]{z} &= (\sqrt[3]{R} * e^{i(\alpha/3)} * e^{j(\beta/3)} * e^{ij(\gamma/3)}) * e^{i(\pi \cdot k + 2\pi \cdot m)/3} * e^{j(\pi \cdot k + 2\pi \cdot p)/3} \\
&= R' * e^{i(\pi \cdot k + 2\pi \cdot m)/3} * e^{j(\pi \cdot k + 2\pi \cdot p)/3}
\end{aligned}$$

$$\begin{aligned}
e^{i(\pi/3)} & \\
e^{i(2\pi/3)} &= e^{i(3\pi/3 - \pi/3)} = (-1) * e^{i(-\pi/3)} \\
e^{i(3\pi/3)} &= (-1) \\
e^{i(4\pi/3)} &= e^{i(3\pi/3 + \pi/3)} = (-1) * e^{i(\pi/3)} \\
e^{i(5\pi/3)} &= e^{i(3\pi/3 + 2\pi/3)} = (-1) * e^{i(2\pi/3)} = e^{i(-\pi/3)}
\end{aligned}$$

$$\begin{aligned}
(\sqrt[3]{z})\langle 0|0|0\rangle &= R' \\
(\sqrt[3]{z})\langle 0|1|0\rangle &= R' * e^{i(2\pi/3)} = R' * (-1) * e^{i(-\pi/3)} \\
(\sqrt[3]{z})\langle 0|2|0\rangle &= R' * e^{i(4\pi/3)} = R' * (-1) * e^{i(\pi/3)} \\
(\sqrt[3]{z})\langle 0|0|1\rangle &= R' * e^{j(2\pi/3)} = R' * (-1) * e^{j(-\pi/3)} \\
(\sqrt[3]{z})\langle 0|1|1\rangle &= R' * e^{i(2\pi/3)} * e^{j(2\pi/3)} = R' * e^{i(-\pi/3)} * e^{j(-\pi/3)} \\
(\sqrt[3]{z})\langle 0|2|1\rangle &= R' * e^{i(4\pi/3)} * e^{j(2\pi/3)} = R' * (-1) * e^{i(\pi/3)} * e^{j(2\pi/3)} = R' * e^{i(\pi/3)} * e^{j(-\pi/3)} \\
(\sqrt[3]{z})\langle 0|0|2\rangle &= R' * e^{j(4\pi/3)} = R' * (-1) * e^{j(\pi/3)} \\
(\sqrt[3]{z})\langle 0|1|2\rangle &= R' * e^{i(2\pi/3)} * e^{j(4\pi/3)} = R' * (-1) * e^{i(2\pi/3)} * e^{j(\pi/3)} = R' * e^{i(-\pi/3)} * e^{j(\pi/3)} \\
(\sqrt[3]{z})\langle 0|2|2\rangle &= R' * e^{i(4\pi/3)} * e^{j(4\pi/3)} = R' * e^{i(\pi/3)} * e^{j(\pi/3)}
\end{aligned}$$

$$\begin{aligned}
(\sqrt[3]{z})\langle 1|0|0\rangle &\doteq R' * e^{i(\pi/3)} * e^{j(\pi/3)} = (\sqrt[3]{z})\langle 0|2|2\rangle \\
(\sqrt[3]{z})\langle 1|1|0\rangle &\doteq R' * e^{i(\pi/3 + 2\pi/3)} * e^{j(\pi/3)} = R' * e^{i(3\pi/3)} * e^{j(\pi/3)} = R' * (-1) * e^{j(\pi/3)} = (\sqrt[3]{z})\langle 0|0|2\rangle \\
(\sqrt[3]{z})\langle 1|2|0\rangle &\doteq R' * e^{i(\pi/3 + 4\pi/3)} * e^{j(\pi/3)} = R' * e^{i(5\pi/3)} * e^{j(\pi/3)} = R' * (-1) * e^{i(2\pi/3)} * e^{j(\pi/3)} = (\sqrt[3]{z})\langle 0|1|2\rangle \\
(\sqrt[3]{z})\langle 1|0|1\rangle &\doteq R' * e^{i(\pi/3)} * e^{j(\pi/3 + 2\pi/3)} = R' * e^{i(\pi/3)} * e^{j(3\pi/3)} = R' * (-1) * e^{i(\pi/3)} = (\sqrt[3]{z})\langle 0|2|0\rangle \\
(\sqrt[3]{z})\langle 1|1|1\rangle &\doteq R' * e^{i(\pi/3 + 2\pi/3)} * e^{j(\pi/3 + 2\pi/3)} = R' * e^{i(3\pi/3)} * e^{j(3\pi/3)} = R' = (\sqrt[3]{z})\langle 0|0|0\rangle \\
(\sqrt[3]{z})\langle 1|2|1\rangle &\doteq R' * e^{i(\pi/3 + 4\pi/3)} * e^{j(\pi/3 + 2\pi/3)} = R' * e^{i(5\pi/3)} * e^{j(3\pi/3)} = R' * e^{i(2\pi/3)} = (\sqrt[3]{z})\langle 0|1|0\rangle \\
(\sqrt[3]{z})\langle 1|0|2\rangle &\doteq R' * e^{i(\pi/3)} * e^{j(\pi/3 + 4\pi/3)} = R' * e^{i(\pi/3)} * e^{j(5\pi/3)} = R' * (-1) * e^{i(\pi/3)} * e^{j(2\pi/3)} = (\sqrt[3]{z})\langle 0|2|1\rangle \\
(\sqrt[3]{z})\langle 1|1|2\rangle &\doteq R' * e^{i(\pi/3 + 2\pi/3)} * e^{j(\pi/3 + 4\pi/3)} = R' * e^{i(3\pi/3)} * e^{j(5\pi/3)} = R' * e^{j(2\pi/3)} = (\sqrt[3]{z})\langle 0|0|1\rangle \\
(\sqrt[3]{z})\langle 1|2|2\rangle &\doteq R' * e^{i(\pi/3 + 4\pi/3)} * e^{j(\pi/3 + 4\pi/3)} = R' * e^{i(5\pi/3)} * e^{j(5\pi/3)} = R' * e^{i(2\pi/3)} * e^{j(2\pi/3)} = (\sqrt[3]{z})\langle 0|1|1\rangle
\end{aligned}$$

$$\begin{aligned}
(\sqrt[3]{z})\langle 0|0|0\rangle &= \sqrt[3]{R} * e^{i(\alpha/3)} * e^{j(\beta/3)} * e^{ij(\gamma/3)} \\
(\sqrt[3]{z})\langle 0|1|0\rangle &= -\sqrt[3]{R} * e^{i(\alpha/3 - \pi/3)} * e^{j(\beta/3)} * e^{ij(\gamma/3)} \\
(\sqrt[3]{z})\langle 0|2|0\rangle &= -\sqrt[3]{R} * e^{i(\alpha/3 + \pi/3)} * e^{j(\beta/3)} * e^{ij(\gamma/3)} \\
(\sqrt[3]{z})\langle 0|0|1\rangle &= -\sqrt[3]{R} * e^{i(\alpha/3)} * e^{j(\beta/3 - \pi/3)} * e^{ij(\gamma/3)} \\
(\sqrt[3]{z})\langle 0|0|2\rangle &= -\sqrt[3]{R} * e^{i(\alpha/3)} * e^{j(\beta/3 + \pi/3)} * e^{ij(\gamma/3)} \\
(\sqrt[3]{z})\langle 0|1|1\rangle &= \sqrt[3]{R} * e^{i(\alpha/3 - \pi/3)} * e^{j(\beta/3 - \pi/3)} * e^{ij(\gamma/3)} \\
(\sqrt[3]{z})\langle 0|1|2\rangle &= \sqrt[3]{R} * e^{i(\alpha/3 - \pi/3)} * e^{j(\beta/3 + \pi/3)} * e^{ij(\gamma/3)} \\
(\sqrt[3]{z})\langle 0|2|1\rangle &= \sqrt[3]{R} * e^{i(\alpha/3 + \pi/3)} * e^{j(\beta/3 - \pi/3)} * e^{ij(\gamma/3)} \\
(\sqrt[3]{z})\langle 0|2|2\rangle &= \sqrt[3]{R} * e^{i(\alpha/3 + \pi/3)} * e^{j(\beta/3 + \pi/3)} * e^{ij(\gamma/3)}
\end{aligned}$$

14 Elementary functions

$$\begin{array}{ll}
 \sin(i \cdot \phi) = i \cdot \sinh(\phi) & \sinh(i \cdot \phi) = i \cdot \sin(\phi) \\
 \sin(j \cdot \phi) = j \cdot \sinh(\phi) & \sinh(j \cdot \phi) = j \cdot \sin(\phi) \\
 \cos(i \cdot \phi) = \cosh(\phi) & \cosh(i \cdot \phi) = \cos(\phi) \\
 \cos(j \cdot \phi) = \cosh(\phi) & \cosh(j \cdot \phi) = \cos(\phi) \\
 \sin(ij \cdot \phi) = ij \cdot \sin(\phi) & \sinh(ij \cdot \phi) = ij \cdot \sinh(\phi) \\
 \cos(ij \cdot \phi) = \cos(\phi) & \cosh(ij \cdot \phi) = \cosh(\phi)
 \end{array}$$

14.1 sin

$$\begin{aligned}
 \sin(a + ib) &= \underline{a} + i\underline{b} \\
 \underline{a} &= \sin(a) * \cosh(b) \\
 \underline{b} &= \cos(a) * \sinh(b)
 \end{aligned}$$

$$\begin{aligned}
 \sin(z) &= \sin(a + ib + jc + ijd) = \underline{a} + i\underline{b} + j\underline{c} + i\underline{d} \\
 \underline{a} &= 1/2 * \sin(a - d) * \cosh(b + c) + 1/2 * \sin(a + d) * \cosh(b - c) \\
 \underline{b} &= 1/2 * \cos(a - d) * \sinh(b + c) + 1/2 * \cos(a + d) * \sinh(b - c) \\
 \underline{c} &= 1/2 * \cos(a - d) * \sinh(b + c) - 1/2 * \cos(a + d) * \sinh(b - c) \\
 \underline{d} &= -1/2 * \sin(a - d) * \cosh(b + c) + 1/2 * \sin(a + d) * \cosh(b - c)
 \end{aligned}$$

14.2 cos

$$\begin{aligned}
 \cos(a + ib) &= \underline{a} + i\underline{b} \\
 \underline{a} &= \cos(a) * \cosh(b) \\
 \underline{b} &= -\sin(a) * \sinh(b)
 \end{aligned}$$

$$\begin{aligned}
 \cos(z) &= \cos(a + ib + jc + ijd) = \underline{a} + i\underline{b} + j\underline{c} + i\underline{d} \\
 \underline{a} &= 1/2 * \cos(a - d) * \cosh(b + c) + 1/2 * \cos(a + d) * \cosh(b - c) \\
 \underline{b} &= -1/2 * \sin(a - d) * \sinh(b + c) - 1/2 * \sin(a + d) * \sinh(b - c) \\
 \underline{c} &= -1/2 * \sin(a - d) * \sinh(b + c) + 1/2 * \sin(a + d) * \sinh(b - c) \\
 \underline{d} &= -1/2 * \cos(a - d) * \cosh(b + c) + 1/2 * \cos(a + d) * \cosh(b - c)
 \end{aligned}$$

14.3 sinh

$$\begin{aligned}
 \sinh(a + ib) &= \underline{a} + i\underline{b} \\
 \underline{a} &= \sinh(a) * \cos(b) \\
 \underline{b} &= \cosh(a) * \sin(b)
 \end{aligned}$$

$$\begin{aligned}
 \sinh(z) &= \sinh(a + ib + jc + ijd) = \underline{a} + i\underline{b} + j\underline{c} + i\underline{d} \\
 \underline{a} &= 1/2 * \sinh(a - d) * \cos(b + c) + 1/2 * \sinh(a + d) * \cos(b - c) \\
 \underline{b} &= 1/2 * \cosh(a - d) * \sin(b + c) + 1/2 * \cosh(a + d) * \sin(b - c) \\
 \underline{c} &= 1/2 * \cosh(a - d) * \sin(b + c) - 1/2 * \cosh(a + d) * \sin(b - c) \\
 \underline{d} &= -1/2 * \sinh(a - d) * \cos(b + c) + 1/2 * \sinh(a + d) * \cos(b - c)
 \end{aligned}$$

14.4 cosh

$$\begin{aligned}
 \cosh(a + ib) &= \underline{a} + i\underline{b} \\
 \underline{a} &= \cosh(a) * \cos(b) \\
 \underline{b} &= \sinh(a) * \sin(b)
 \end{aligned}$$

$$\begin{aligned}
 \cosh(z) &= \cosh(a + ib + jc + ijd) = \underline{a} + i\underline{b} + j\underline{c} + i\underline{d} \\
 \underline{a} &= 1/2 * \cosh(a - d) * \cos(b + c) + 1/2 * \cosh(a + d) * \cos(b - c) \\
 \underline{b} &= 1/2 * \sinh(a - d) * \sin(b + c) + 1/2 * \sinh(a + d) * \sin(b - c) \\
 \underline{c} &= 1/2 * \sinh(a - d) * \sin(b + c) - 1/2 * \sinh(a + d) * \sin(b - c) \\
 \underline{d} &= -1/2 * \cosh(a - d) * \cos(b + c) + 1/2 * \cosh(a + d) * \cos(b - c)
 \end{aligned}$$

14.5 tan & Co.

$$\tan(z) = \sin(z) / \cos(z)$$

$$\cot(z) = \cos(z) / \sin(z)$$

$$\tanh(z) = \sinh(z) / \cosh(z)$$

$$\coth(z) = \cosh(z) / \sinh(z)$$

$$\sec(z) = 1 / \cos(z)$$

$$\operatorname{cosec}(z) = 1 / \sin(z)$$

$$\operatorname{sech}(z) = 1 / \cosh(z)$$

$$\operatorname{cosech}(z) = 1 / \sinh(z)$$

14.6 inverse functions < i >

$$\operatorname{asin}(z) = \pi/2 - i \cdot \ln(z + \sqrt{z^2 - 1}) = -i \cdot \ln(iz + \sqrt{1 - z^2})$$

$$\operatorname{acos}(z) = i \cdot \ln(z + \sqrt{z^2 - 1})$$

$$\operatorname{asinh}(z) = \ln(z + \sqrt{z^2 + 1})$$

$$\operatorname{acosh}(z) = \ln(z + \sqrt{z^2 - 1})$$

$$\operatorname{asec}(z) = \operatorname{acos}\left(\frac{1}{z}\right) = i \cdot \ln\left(\frac{1}{z} + \sqrt{\frac{1}{z^2} - 1}\right)$$

$$\operatorname{acosec}(z) = \operatorname{asin}\left(\frac{1}{z}\right) = \frac{\pi}{2} - i \cdot \ln\left(\frac{1}{z} + \sqrt{\frac{1}{z^2} - 1}\right)$$

$$\operatorname{asech}(z) = \operatorname{acosh}\left(\frac{1}{z}\right) = \ln\left(\frac{1}{z} + \sqrt{\frac{1}{z^2} - 1}\right)$$

$$\operatorname{acosech}(z) = \operatorname{asinh}\left(\frac{1}{z}\right) = \ln\left(\frac{1}{z} + \sqrt{\frac{1}{z^2} + 1}\right)$$

$$\operatorname{atan}(z) = -\frac{i}{2} \ln\left(\frac{i-z}{i+z}\right) = -\frac{i}{2} \ln\left(\frac{1+iz}{1-iz}\right)$$

$$\operatorname{acot}(z) = -\frac{i}{2} \ln\left(\frac{z+i}{z-i}\right) = -\frac{i}{2} \ln\left(\frac{iz-1}{iz+1}\right)$$

$$\operatorname{atanh}(z) = \frac{1}{2} \ln\left(\frac{1+z}{1-z}\right)$$

$$\operatorname{acoth}(z) = \frac{1}{2} \ln\left(\frac{z+1}{z-1}\right)$$

14.7 normalized functions

$$nF(z) \equiv F(z) / |F(z)|$$

$$n\sin(z) = \sin(z) / |\sin(z)|$$

$$n\cos(z) = \cos(z) / |\cos(z)|$$

$$n\tan(z) = \tan(z) / |\tan(z)|$$

$$n\cot(z) = \cot(z) / |\cot(z)|$$

...

14.8 exp

$$\begin{aligned}\exp(z) &= e^z = e^{a+ib+jc+ijd} = e^a * e^{ib+jc+ijd} \\ \text{nexp}(z) &= e^z / |e^z| = e^{ib+jc+ijd}\end{aligned}$$

14.9 ln

$$\begin{aligned}\ln(z) &= \ln(R * e^{i\alpha+j\beta+ij\gamma}) = \ln(R) + i\alpha + j\beta + ij\gamma \\ \text{Ln}(z) &= \ln(R) + i(\alpha + \pi \cdot k + 2\pi \cdot m) + j(\beta + \pi \cdot k + 2\pi \cdot p) + ij\gamma \\ k &= 0, 1 \\ m &= 0, 1, \dots \\ p &= 0, 1, \dots\end{aligned}$$

$$\begin{aligned}\text{Ln}(z)_{<0|0|0>} &= \ln(R) + i\alpha + j\beta + ij\gamma \\ \text{Ln}(z)_{<0|m|p>} &= \ln(R) + i(\alpha + 2\pi \cdot m) + j(\beta + 2\pi \cdot p) + ij\gamma \\ \text{Ln}(z)_{<1|m|p>} &= \ln(R) + i(\alpha + \pi + 2\pi \cdot m) + j(\beta + \pi + 2\pi \cdot p) + ij\gamma\end{aligned}$$

15 Alternative notation

$$z = a + ib + jc + id = R * e^{i\alpha + j\beta + ij\gamma}$$

$$z = a_0 \cdot (1 + ij) / 2 + b_0 \cdot (i - j) / 2 + c_0 \cdot (1 - ij) / 2 + d_0 \cdot (i + j) / 2$$

$$(1 + ij) * (1 + ij) = 1 + ij + ij + 1 = 2 \cdot (1 + ij)$$

$$(1 + ij) * (i - j) = i - j - j + i = 2 \cdot (i - j)$$

$$(1 + ij) * (1 - ij) = 1 - ij + ij - 1 = 0$$

$$(1 + ij) * (i + j) = i + j - j - i = 0$$

$$(i - j) * (1 + ij) = i - j - j + i = 2 \cdot (i - j)$$

$$(i - j) * (i - j) = -1 - ij - ij - 1 = -2 \cdot (1 + ij)$$

$$(i - j) * (1 - ij) = i + j - j - i = 0$$

$$(i - j) * (i + j) = -1 + ij - ij + 1 = 0$$

$$(1 - ij) * (1 + ij) = 1 + ij - ij - 1 = 0$$

$$(1 - ij) * (i - j) = i - j + j - i = 0$$

$$(1 - ij) * (1 - ij) = 1 - ij - ij + 1 = 2 \cdot (1 - ij)$$

$$(1 - ij) * (i + j) = i + j + j + i = 2 \cdot (i + j)$$

$$(i + j) * (1 + ij) = i - j + j - i = 0$$

$$(i + j) * (i - j) = -1 - ij - ij + 1 = 0$$

$$(i + j) * (1 - ij) = i + j + j + i = 2 \cdot (i + j)$$

$$(i + j) * (i + j) = -1 + ij + ij - 1 = -2 \cdot (1 - ij)$$

15.1

$$\begin{cases} a = (a_0 + c_0) / 2 \\ b = (d_0 + b_0) / 2 \\ c = (d_0 - b_0) / 2 \\ d = (a_0 - c_0) / 2 \end{cases}$$

$$\begin{cases} a_0 = a + d \\ b_0 = b - c \\ c_0 = a - d \\ d_0 = b + c \end{cases}$$

15.2

$$R = \sqrt[4]{(a_0^2 + b_0^2) * (c_0^2 + d_0^2)} = \sqrt[4]{((a + d)^2 + (b - c)^2) * ((a - d)^2 + (b + c)^2)}$$

$$\gamma = \frac{1}{4} \ln \frac{(a_0^2 + b_0^2)}{(c_0^2 + d_0^2)} = \frac{1}{4} \ln \frac{(a + d)^2 + (b - c)^2}{(a - d)^2 + (b + c)^2}$$

$$\alpha = \frac{1}{2} [\arg(a_0, b_0) + \arg(c_0, d_0)] = \frac{1}{2} [\arg(a + d, b - c) + \arg(a - d, b + c)]$$

$$\beta = \frac{1}{2} [\arg(c_0, d_0) - \arg(a_0, b_0)] = \frac{1}{2} [\arg(a - d, b + c) - \arg(a + d, b - c)]$$

$$\arg(x, y) = \arctan(y, x) = \arctan(y : x) = \arctan(y/x)$$

15.3

$$\begin{cases} a_0 = a + d = R * e^{+\gamma} * \cos(\alpha - \beta) \\ b_0 = b - c = R * e^{+\gamma} * \sin(\alpha - \beta) \\ c_0 = a - d = R * e^{-\gamma} * \cos(\alpha + \beta) \\ d_0 = b + c = R * e^{-\gamma} * \sin(\alpha + \beta) \end{cases}$$

$$\begin{cases} R * e^{+\gamma} = \sqrt{a_0^2 + b_0^2} = \sqrt{(a + d)^2 + (b - c)^2} \\ R * e^{-\gamma} = \sqrt{c_0^2 + d_0^2} = \sqrt{(a - d)^2 + (b + c)^2} \end{cases}$$

$$\begin{cases} \alpha - \beta = \arg(a_0, b_0) = \arg(a + d, b - c) \\ \alpha + \beta = \arg(c_0, d_0) = \arg(a - d, b + c) \end{cases}$$

16 Dimension reduction

$$w = (a + ib) + j \cdot (c + id) = r * e^{i\phi} + j \cdot \rho * e^{i\psi}$$

$$\phi = \psi \Rightarrow$$

$$w = a + i \cdot b + j \cdot c + ij \cdot d = (x, y, z)$$

$$R^2 = a^2 + b^2 + c^2 + d^2 = x^2 + y^2 + z^2$$

16.1 xy:z<..>

$$z' = z / \sqrt{x^2 + y^2}$$

16.1.1 xy:z<ab>

$$w = (x + iy) + j \cdot (x + iy) \cdot z' = (x + iy) + j \cdot (x + iy) \cdot z / \sqrt{x^2 + y^2}$$

$$w = x + i \cdot y + j \cdot x \cdot z / \sqrt{x^2 + y^2} + ij \cdot y \cdot z / \sqrt{x^2 + y^2} = a + i \cdot b + j \cdot c + ij \cdot d$$

$$\begin{aligned} a &= x & x &= a \\ b &= y & y &= b \\ c &= x \cdot z / \sqrt{x^2 + y^2} & z &= c \cdot \sqrt{a^2 + b^2} / a \\ d &= y \cdot z / \sqrt{x^2 + y^2} & z &= d \cdot \sqrt{a^2 + b^2} / b \end{aligned}$$

$$x = y \Rightarrow a = x \quad b = y \quad c = \text{sign}(x) \cdot z / \sqrt{2} \quad d = \text{sign}(y) \cdot z / \sqrt{2}$$

$$\tan \phi = \tan \psi = y / x$$

16.1.2 xy:z<cd>

$$w = (x + iy) \cdot z' + j \cdot (x + iy) = (x + iy) \cdot z / \sqrt{x^2 + y^2} + j \cdot (x + iy)$$

$$w = x \cdot z / \sqrt{x^2 + y^2} + i \cdot y \cdot z / \sqrt{x^2 + y^2} + jx + i jy = a + i \cdot b + j \cdot c + ij \cdot d$$

$$\begin{aligned} a &= x \cdot z / \sqrt{x^2 + y^2} & x &= c \\ b &= y \cdot z / \sqrt{x^2 + y^2} & y &= d \\ c &= x & z &= a \cdot \sqrt{c^2 + d^2} / c \\ d &= y & z &= b \cdot \sqrt{c^2 + d^2} / d \end{aligned}$$

$$x = y \Rightarrow a = \text{sign}(x) \cdot z / \sqrt{2} \quad b = \text{sign}(y) \cdot z / \sqrt{2} \quad c = x \quad d = y$$

$$\tan \phi = \tan \psi = y / x$$

16.1.3 xy:z<ba>

$$w = (y + ix) + j \cdot (y + ix) \cdot z' = (y + ix) + j \cdot (y + ix) \cdot z / \sqrt{x^2 + y^2}$$

$$w = y + i \cdot x + j \cdot y \cdot z / \sqrt{x^2 + y^2} + ij \cdot x \cdot z / \sqrt{x^2 + y^2} = a + i \cdot b + j \cdot c + ij \cdot d$$

$$\begin{aligned} a &= y & x &= b \\ b &= x & y &= a \\ c &= y \cdot z / \sqrt{x^2 + y^2} & z &= c \cdot \sqrt{a^2 + b^2} / a \\ d &= x \cdot z / \sqrt{x^2 + y^2} & z &= d \cdot \sqrt{a^2 + b^2} / b \end{aligned}$$

$$x = y \Rightarrow a = y \quad b = x \quad c = \text{sign}(y) \cdot z / \sqrt{2} \quad d = \text{sign}(x) \cdot z / \sqrt{2}$$

$$\tan \phi = \tan \psi = x / y$$

16.1.4 xy:z<dc>

$$w = (y + ix) \cdot z' + j \cdot (y + ix) = (y + ix) \cdot z / \sqrt{x^2 + y^2} + j \cdot (y + ix)$$

$$w = y \cdot z / \sqrt{x^2 + y^2} + i \cdot x \cdot z / \sqrt{x^2 + y^2} + jy + i jx = a + i \cdot b + j \cdot c + ij \cdot d$$

$$\begin{aligned} a &= y \cdot z / \sqrt{x^2 + y^2} & x &= d \\ b &= x \cdot z / \sqrt{x^2 + y^2} & y &= c \\ c &= y & z &= a \cdot \sqrt{c^2 + d^2} / c \\ d &= x & z &= b \cdot \sqrt{c^2 + d^2} / d \end{aligned}$$

$$x = y \Rightarrow a = \text{sign}(y) \cdot z / \sqrt{2} \quad b = \text{sign}(x) \cdot z / \sqrt{2} \quad c = y \quad d = x$$

$$\tan \phi = \tan \psi = x / y$$

16.1.5 xy:z<ac>

$$w = (x + jy) + i \cdot (x + jy) \cdot z' = (x + jy) + i \cdot (x + jy) \cdot z / \sqrt{x^2 + y^2}$$

$$w = x + i \cdot x \cdot z / \sqrt{x^2 + y^2} + j \cdot y + ij \cdot y \cdot z / \sqrt{x^2 + y^2} = a + i \cdot b + j \cdot c + ij \cdot d$$

$$\begin{aligned} a &= x & x &= a \\ b &= x \cdot z / \sqrt{x^2 + y^2} & y &= c \\ c &= y & z &= b \cdot \sqrt{a^2 + b^2} / a \\ d &= y \cdot z / \sqrt{x^2 + y^2} & z &= d \cdot \sqrt{a^2 + b^2} / c \end{aligned}$$

$$x = y \Rightarrow a = x \quad b = \text{sign}(x) \cdot z / \sqrt{2} \quad c = y \quad d = \text{sign}(y) \cdot z / \sqrt{2}$$

$$\tan \phi = \tan \psi = z / \sqrt{x^2 + y^2}$$

16.1.6 xy:z<ca>

$$w = (y + jx) + i \cdot (y + jx) \cdot z' = (y + jx) + i \cdot (y + jx) \cdot z / \sqrt{x^2 + y^2}$$

$$w = y + i \cdot y \cdot z / \sqrt{x^2 + y^2} + j \cdot x + ij \cdot x \cdot z / \sqrt{x^2 + y^2} = a + i \cdot b + j \cdot c + ij \cdot d$$

$$\begin{aligned} a &= y & x &= c \\ b &= y \cdot z / \sqrt{x^2 + y^2} & y &= a \\ c &= x & z &= b \cdot \sqrt{a^2 + b^2} / a \\ d &= x \cdot z / \sqrt{x^2 + y^2} & z &= d \cdot \sqrt{a^2 + b^2} / c \end{aligned}$$

$$x = y \Rightarrow a = y \quad b = \text{sign}(y) \cdot z / \sqrt{2} \quad c = x \quad d = \text{sign}(x) \cdot z / \sqrt{2}$$

$$\tan \phi = \tan \psi = z / \sqrt{x^2 + y^2}$$

16.1.7 xy:z<bd>

$$w = (x + jy) \cdot z' + i \cdot (x + jy) = (x + jy) \cdot z / \sqrt{x^2 + y^2} + i \cdot (x + jy)$$

$$w = x \cdot z / \sqrt{x^2 + y^2} + ix + j \cdot y \cdot z / \sqrt{x^2 + y^2} + ijy = a + i \cdot b + j \cdot c + ij \cdot d$$

$$\begin{aligned} a &= x \cdot z / \sqrt{x^2 + y^2} & x &= b \\ b &= x & y &= d \\ c &= y \cdot z / \sqrt{x^2 + y^2} & z &= a \cdot \sqrt{c^2 + d^2} / b \\ d &= y & z &= c \cdot \sqrt{c^2 + d^2} / d \end{aligned}$$

$$x = y \Rightarrow a = \text{sign}(x) \cdot z / \sqrt{2} \quad b = x \quad c = \text{sign}(y) \cdot z / \sqrt{2} \quad d = y$$

$$\tan \phi = \tan \psi = \sqrt{x^2 + y^2} / z$$

16.1.8 xy:z<db>

$$w = (y + jx) \cdot z' + i \cdot (y + jx) = (y + jx) \cdot z / \sqrt{x^2 + y^2} + i \cdot (y + jx)$$

$$w = y \cdot z / \sqrt{x^2 + y^2} + iy + j \cdot x \cdot z / \sqrt{x^2 + y^2} + ijx = a + i \cdot b + j \cdot c + ij \cdot d$$

$$\begin{aligned} a &= y \cdot z / \sqrt{x^2 + y^2} & x &= d \\ b &= y & y &= b \\ c &= x \cdot z / \sqrt{x^2 + y^2} & z &= a \cdot \sqrt{c^2 + d^2} / b \\ d &= x & z &= c \cdot \sqrt{c^2 + d^2} / d \end{aligned}$$

$$x = y \Rightarrow a = \text{sign}(y) \cdot z / \sqrt{2} \quad b = y \quad c = \text{sign}(x) \cdot z / \sqrt{2} \quad d = x$$

$$\tan \phi = \tan \psi = \sqrt{x^2 + y^2} / z$$

16.2 $yz:x\langle\cdot\rangle$

$$x' = x / \sqrt{y^2 + z^2}$$

$$\begin{aligned}yz : x \langle ab \rangle & w = (y + iz) + j \cdot (y + iz) \cdot x' \\yz : x \langle cd \rangle & w = (y + iz) \cdot x' + j \cdot (y + iz) \\yz : x \langle ba \rangle & w = (z + iy) + j \cdot (z + iy) \cdot x' \\yz : x \langle dc \rangle & w = (z + iy) \cdot x' + j \cdot (z + iy) \\yz : x \langle ac \rangle & w = (y + jz) + i \cdot (y + jz) \cdot x' \\yz : x \langle ca \rangle & w = (z + jy) + i \cdot (z + jy) \cdot x' \\yz : x \langle bd \rangle & w = (y + jz) \cdot x' + i \cdot (y + jz) \\yz : x \langle db \rangle & w = (z + jy) \cdot x' + i \cdot (z + jy)\end{aligned}$$

16.3 $zx:y\langle\cdot\rangle$

$$y' = y / \sqrt{x^2 + z^2}$$

$$\begin{aligned}zx : y \langle ab \rangle & w = (x + iz) + j \cdot (x + iz) \cdot y' \\zx : y \langle cd \rangle & w = (x + iz) \cdot y' + j \cdot (x + iz) \\zx : y \langle ba \rangle & w = (z + ix) + j \cdot (z + ix) \cdot y' \\zx : y \langle dc \rangle & w = (z + ix) \cdot y' + j \cdot (z + ix) \\zx : y \langle ac \rangle & w = (x + jz) + i \cdot (x + jz) \cdot y' \\zx : y \langle ca \rangle & w = (z + jx) + i \cdot (z + jx) \cdot y' \\zx : y \langle bd \rangle & w = (x + jz) \cdot y' + i \cdot (x + jz) \\zx : y \langle db \rangle & w = (z + jx) \cdot y' + i \cdot (z + jx)\end{aligned}$$

17 Dimension reduction: $xy:z \langle ab \rangle$

$$w = (a + i \cdot b) + j \cdot (c + i \cdot d) = r * e^{i\phi} + j \cdot \rho * e^{i\psi}$$

$$\phi = \psi$$

$$w = x + i \cdot y + j \cdot x \cdot z / \sqrt{x^2 + y^2} + ij \cdot y \cdot z / \sqrt{x^2 + y^2}$$

$$\begin{aligned} a &= x & x &= a \\ b &= y & y &= b \\ c &= x \cdot z / \sqrt{x^2 + y^2} & z &= c \cdot \sqrt{a^2 + b^2} / a \\ d &= y \cdot z / \sqrt{x^2 + y^2} & z &= d \cdot \sqrt{a^2 + b^2} / b \end{aligned}$$

$$\begin{aligned} x = y \neq 0 &\Rightarrow a = x & b = y & c = \text{sign}(x) \cdot z / \sqrt{2} & d = \text{sign}(y) \cdot z / \sqrt{2} \\ x = y = 0 &\Rightarrow a = 0 & b = 0 & c \stackrel{\text{def}}{=} z / \sqrt{2} & d \stackrel{\text{def}}{=} z / \sqrt{2} \end{aligned}$$

$$d = c \cdot \frac{y}{x}$$

$$a \cdot d = b \cdot c = \frac{x \cdot y \cdot z}{\sqrt{x^2 + y^2}}$$

$$\begin{aligned} a + d &= (x \cdot \sqrt{x^2 + y^2} + y \cdot z) / \sqrt{x^2 + y^2} \\ a - d &= (x \cdot \sqrt{x^2 + y^2} - y \cdot z) / \sqrt{x^2 + y^2} \\ b + c &= (y \cdot \sqrt{x^2 + y^2} + x \cdot z) / \sqrt{x^2 + y^2} \\ b - c &= (y \cdot \sqrt{x^2 + y^2} - x \cdot z) / \sqrt{x^2 + y^2} \end{aligned}$$

$$\tan \phi = \tan \psi = y / x$$

17.1 Conjugate

$$\begin{aligned} w &= (a + ib) + j(c + id) = a + ib + jc + ijd \\ \bar{w}_{ij} &= (a - ib) - j(c - id) = a - ib - jc + ijd \\ w * \bar{w}_{ij} &= R^2 = a^2 + b^2 + c^2 + d^2 = x^2 + y^2 + z^2 \end{aligned}$$

17.2 Exponential form

$$w = (a + ib) + j(c + id) = r * e^{i\phi} + j \cdot \rho * e^{i\psi}$$

$$w = |w| * e^{i\alpha + j\beta + ij\gamma} = R * e^{i\alpha + j\beta + ij\gamma}$$

$$\begin{aligned} \phi &= \psi \\ \gamma &= 0 \end{aligned}$$

$$w = |w| * e^{i\alpha + j\beta} = R * e^{i\alpha + j\beta} = R * (\cos \alpha + i \sin \alpha) * (\cos \beta + j \sin \beta)$$

$$a = R \cdot \cos \alpha \cdot \cos \beta$$

$$b = R \cdot \sin \alpha \cdot \cos \beta$$

$$c = R \cdot \cos \alpha \cdot \sin \beta$$

$$d = R \cdot \sin \alpha \cdot \sin \beta$$

$$R^2 = a^2 + b^2 + c^2 + d^2 = x^2 + y^2 + z^2$$

$$\begin{cases} \tan(\alpha - \beta) = \frac{b - c}{a + d} = \frac{y \cdot \sqrt{x^2 + y^2} - x \cdot z}{x \cdot \sqrt{x^2 + y^2} + y \cdot z} = \arg(a + d, b - c) \\ \tan(\alpha + \beta) = \frac{b + c}{a - d} = \frac{y \cdot \sqrt{x^2 + y^2} + x \cdot z}{x \cdot \sqrt{x^2 + y^2} - y \cdot z} = \arg(a - d, b + c) \end{cases}$$

$$\alpha = \frac{1}{2} [\arg(a + d, b - c) + \arg(a - d, b + c)]$$

$$\beta = \frac{1}{2} [\arg(a - d, b + c) - \arg(a + d, b - c)]$$

$$\arg(x, y) = \arctan(y, x) = \arctan(y : x) = \arctan(y/x)$$